University of Groningen

Secondary Frequency Control With On-Off Load Side Participation in Power Networks

Kasis, Andreas; Monshizadeh, Nima; Lestas, Ioannis

Published in:
IEEE Transactions on Control of Network Systems

DOI:
[10.1109/TCNS.2019.2934386](https://doi.org/10.1109/TCNS.2019.2934386)

IMPORTANT NOTE: You are advised to consult the publisher's version (publisher's PDF) if you wish to cite from it. Please check the document version below.

Document Version
Publisher's PDF, also known as Version of record

Publication date:
2020

[Link to publication in University of Groningen/UMCG research database](#)

Citation for published version (APA):

Kasis, A., Monshizadeh, N., & Lestas, I. (2020). Secondary Frequency Control With On-Off Load Side Participation in Power Networks. *IEEE Transactions on Control of Network Systems*, 7(2), 603-613. [8792949]. <https://doi.org/10.1109/TCNS.2019.2934386>

Copyright

Other than for strictly personal use, it is not permitted to download or to forward/distribute the text or part of it without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license (like Creative Commons).

The publication may also be distributed here under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license. More information can be found on the University of Groningen website: <https://www.rug.nl/library/open-access/self-archiving-pure/taverne-amendment>.

Take-down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Downloaded from the University of Groningen/UMCG research database (Pure): <http://www.rug.nl/research/portal>. For technical reasons the number of authors shown on this cover page is limited to 10 maximum.

Secondary Frequency Control With On–Off Load Side Participation in Power Networks

Andreas Kasis , Nima Monshizadeh , and Ioannis Lestas

Abstract—We study the problem of decentralized secondary frequency regulation in power networks where ancillary services are provided via on–off load-side participation. We initially consider on–off loads that switch when prescribed frequency thresholds are exceeded, together with a large class of passive continuous dynamics for generation and demand. The considered on–off loads are able to assist existing secondary frequency control mechanisms and return to their nominal operation when the power system is restored to its normal operation, a highly desirable feature that minimizes users' disruption. We show that system stability is not compromised despite the switching nature of the loads. However, such control policies are prone to chattering, which limits the practicality of these schemes. As a remedy to this problem, we propose a hysteretic on–off policy where loads switch on and off at different frequency thresholds and show that stability guarantees are retained when the same decentralized passivity conditions for continuous generation and demand hold. Several relevant examples are discussed to demonstrate the applicability of the proposed results. Furthermore, we verify our analytic results by using numerical investigations on the Northeast Power Coordinating Council (NPCC) 140-bus system.

Index Terms—Smart grids, power system control, decentralized control, control of networks, hybrid systems, demand-side management.

I. INTRODUCTION

Motivation and literature survey: It is anticipated that renewable sources of generation will increase their penetration in power networks in the near future [2], [3]. This is expected to introduce intermittency in the power generated, resulting in additional challenges in the real-time operation of power networks that need to be addressed.

A main objective in the operation of a power system is to ensure that generation matches demand in real time. This is achieved by means of primary and secondary frequency control

schemes, with the latter also ensuring that the frequency returns to its nominal value (50 or 60 Hz). Secondary frequency control is traditionally performed by having the generation side following demand [4]. However, a large penetration of renewable sources of generation limits the controllability of generation and at the same time makes the system more sensitive to disturbances due to the reduced system inertia [5]. Controllable loads are considered by many as a promising solution to counterbalance intermittent generation, being able to adapt their demand based on frequency deviations, providing fast response at urgencies. Recently, various research studies focused on the inclusion of controllable demand to aid both primary control as in [6]–[11] and secondary control as in [12]–[14].

Further from providing ancillary services at urgencies, it is also desired that controllable loads are nondisruptive; i.e., their assistance should have a negligible effect on users' comfort; see, e.g., [15]. Nondisruptive load-side control schemes ensure that loads alter their demand at urgencies but return to their normal operation when the danger for the network has been surpassed. Moreover, in many occasions, a realistic representation of loads involves only a discrete set of possible demand values, e.g., on and off states. Hence, incorporating on–off controllable loads that appropriately react to frequency deviations in power networks is of particular interest in load-side participation schemes.

Contribution: As already mentioned, the incorporation of controllable demand within the power network has been extensively studied in the literature [6]–[14]. However, the existing theoretical studies consider power networks with controllable loads that vary continuously with deviations in frequency. These are, thus, unable to capture discontinuities, which are relevant when loads can take only a discrete number of states, e.g., on and off, as is often the case in practice. This study provides analytical results that allow on–off loads to contribute to frequency control within a power network with a general network topology, when the continuous part of the generation/demand dynamics, which are allowed to be heterogeneous and of higher order, satisfy certain decentralized passivity conditions. In particular, by the prospect of loads providing ancillary service to the power network in a decentralized way and the desire that users' comfort will be distorted for only short periods of time, we consider controllable on–off loads that switch when some frequency deviation is reached so that they assist the network at urgencies (i.e., when large frequency deviations are experienced) and otherwise return to their original operation. It will be shown that the inclusion of such loads does not compromise

Manuscript received May 10, 2019; accepted July 18, 2019. Date of publication August 9, 2019; date of current version June 12, 2020. This work was supported by ERC starting grant 679774. A preliminary version of this paper was presented at the 56th IEEE Conference on Decision and Control, Melbourne, Vic., Australia, December 2017. Recommended by Associate Editor M. R. Jovanovic. (Corresponding author: Ioannis Lestas.)

A. Kasis and I. Lestas are with the Department of Engineering, University of Cambridge, Cambridge CB2 1PZ U.K. (e-mail: ak647@cam.ac.uk; icl20@cam.ac.uk).

N. Monshizadeh is with the Engineering and Technology Institute, University of Groningen, Groningen 9747AG, The Netherlands (e-mail: n.monshizadeh@rug.nl).

Digital Object Identifier 10.1109/TCNS.2019.2934386

the stability of the power network, and it results in enhanced frequency performance. However, it will be observed that such controllable loads may switch arbitrarily fast within a finite interval of time, or, in other words, they may exhibit chattering. To avoid this phenomenon, we propose on–off loads with hysteretic dynamics where loads switch on and off at different frequency thresholds. As it will be analytically shown in this paper, unlike (instantaneous) on–off loads, hysteretic loads do not induce chattering behavior. Furthermore, we show that stability guarantees can be provided when such schemes are used within the power network. It should be noted that hysteretic dynamics increase the complexity of the analysis, as they render the underlying dynamical system a hybrid system, thus requiring appropriate analysis tools to be employed [16]. Various examples are provided to demonstrate the applicability of the results presented. Moreover, we provide a numerical validation of our analytic results on the Northeast Power Coordinating Council (NPCC) 140-bus system, where it is demonstrated that the incorporation of frequency-dependent on–off loads provides improved frequency response by reducing its overshoot.

Paper structure: The structure of this paper is as follows. Section II includes some basic notation and preliminaries, and in Sections III and IV we present the power network model and the considered continuous generation and demand dynamics, respectively. In Section V, we study the behavior of controllable demand that switches on/off whenever certain frequency thresholds are met and present our results concerning network stability. We also discuss in this section that problematic chattering behavior can be observed. In Section VI, we consider controllable loads with hysteretic patterns and show that the stability results extend to this case while avoiding chattering. In Section VII, we provide relevant examples of continuous generation and demand dynamics, including higher order schemes that fit within the proposed framework and allow for stability guarantees to be deduced when discontinuous and hysteretic loads are also considered. Numerical investigations of the results are provided in Section VIII. Finally, conclusions are drawn in Section IX. The appendix includes the proofs of the results.

II. NOTATION

Real numbers are denoted by $\mathbb{R}$, and the set of n -dimensional vectors with real entries is denoted by $\mathbb{R}^n$. The set of nonnegative real numbers is denoted by $\mathbb{R}_{\geq 0}$. The set of natural numbers, including zero, is denoted by $\mathbb{N}_0$. We use $\mathbf{0}_n$ to denote the $n \times 1$ vector with all elements equal to 0. A function $f : \mathbb{R}^n \rightarrow \mathbb{R}$ is said to be positive definite if $f(0) = 0$ and $f(x) > 0$ for every nonzero $x \in \mathbb{R}^n$. It is positive semidefinite if the inequality > 0 is replaced by ≥ 0 . For a discrete set Σ , let $|\Sigma|$ denote its cardinality. For a scalar-valued function $V(x)$, $V : \mathbb{R}^n \rightarrow \mathbb{R}$, and we denote its gradient by $\frac{\partial V}{\partial x}$. We denote by $\text{sgn}(x)$ the function that takes the value of 1 when x is nonnegative and -1 otherwise. The Laplace transform of a signal $h(t)$ is denoted by $\hat{h}(s) = \int_0^\infty e^{-st} h(t) dt$. A set $M \subset \mathbb{R}^n$ is said to be invariant with respect to a system $\dot{x} = f(x)$, where $f : \mathbb{R}^n \rightarrow \mathbb{R}^n$ is locally Lipschitz if $x(0) \in M$ implies that the solution

$x(t)$ satisfies $x(t) \in M \quad \forall t \in \mathbb{R}$. Finally, the closure of a set S is denoted by $\bar{S}$.

III. NETWORK MODEL

We describe the power network model by a connected graph (N, E) where $N = \{1, 2, \dots, |N|\}$ is the set of buses and $E \subseteq N \times N$ the set of transmission lines connecting the buses. Furthermore, we use (i, j) to denote the link connecting buses i and j and assume that the graph (N, E) is directed with arbitrary orientation, so that if $(i, j) \in E$ then $(j, i) \notin E$. For each $j \in N$, we use $i : i \rightarrow j$ and $k : j \rightarrow k$ to denote the sets of buses that are predecessors and successors of bus j , respectively. The following assumptions are made for the network.

- 1) Bus voltage magnitudes are $|V_j| = 1$ per-unit (p.u.) for each $j \in N$.
- 2) Lines $(i, j) \in E$ are lossless and characterized by their susceptances $B_{ij} = B_{ji} > 0$.
- 3) Reactive-power flows do not affect the bus voltage's phase angles and frequencies.

Remark 1: The above assumptions are standard in secondary frequency control studies, e.g. [6], [17]–[19] and are valid when medium to high voltages are considered [20] or when tight voltage control is present. In Section VIII, we also demonstrate our results in a realistic simulation study.

We use swing equations, see e.g. [20], to describe the frequency dynamics at each bus

$$\dot{\eta}_{ij} = \omega_i - \omega_j, \quad (i, j) \in E \quad (1a)$$

$$M_j \dot{\omega}_j = -p_j^L + p_j^M - (d_j^c + d_j^u) - \sum_{k:j \rightarrow k} p_{jk} + \sum_{i:i \rightarrow j} p_{ij}, \quad j \in N \quad (1b)$$

$$p_{ij} = B_{ij} \sin \eta_{ij}, \quad (i, j) \in E. \quad (1c)$$

In system (1), the time-dependent variables p_j^M and ω_j represent, respectively, the mechanical power injection and the deviation from the nominal¹ frequency at bus j . The time-dependent variable d_j^c represents the deviation of the frequency-dependent controllable load at bus j from its nominal² value. The quantity d_j^u is also a time-dependent variable that represents the uncontrollable frequency-dependent load and generation damping present at bus j . Furthermore, the quantities η_{ij} and p_{ij} are time-dependent variables that represent, respectively, the power angle difference and the power transmitted from bus i to bus j . The constant $M_j > 0$ denotes the generator inertia, and the constant p_j^L includes the frequency-independent load and the nominal value of the controllable load at bus j . We study the response of system (1) at a step change in the frequency-independent uncontrollable demand p_j^L at each bus.

¹The nominal value of frequency is equal to 50 Hz (or 60 Hz)

²In particular, $d_j^c(t) = \hat{d}_j^c(t) - d_j^{\text{nom}}$ where $\hat{d}_j^c(t)$ is the controllable load and d_j^{nom} a constant nominal value chosen by the users. To simplify the presentation, d_j^{nom} is included within the constant p_j^L .

IV. PASSIVE CONTINUOUS DYNAMICS

Before we study the effect of on–off loads in the power network, we consider, in this section, a general class of continuous passive nonlinear dynamics for generation and demand. Existing studies, e.g., [9] and [21], demonstrated the stability of the power network when such dynamics are present. In the following sections, we demonstrate that the generation and demand dynamics presented in this section allow the incorporation of on–off loads without compromising stability, despite their non-smooth and hybrid nature. The practical relevance and generality of the class of dynamics described in this section will be demonstrated with various examples in Section VII.

A. Dynamics for Generation and Demand

For convenience in the analysis, we define a net power supply variable s_j that represents the aggregation of generation and uncontrollable frequency-dependent demand at bus j , given by

$$s_j = p_j^M - d_j^u, j \in N. \quad (2)$$

To incorporate a general class of dynamics for the net supply variables, we assume that s_j is the output of a nonlinear system, namely

$$\begin{aligned} \dot{x}_j^s &= f_j(x_j^s, -\omega_j) \\ s_j &= g_j(x_j^s, -\omega_j) \end{aligned} \quad (3)$$

for each $j \in N$, where $x_j^s \in \mathbb{R}^{n_j}$ is the state of the system, and $f_j : \mathbb{R}^{n_j} \times \mathbb{R} \rightarrow \mathbb{R}^{n_j}$ and $g_j : \mathbb{R}^{n_j} \times \mathbb{R} \rightarrow \mathbb{R}$ are globally Lipschitz for each $j \in N$.

B. Equilibrium Analysis

When $d^c(t) = \mathbf{0}_{|N|}$, $t \in \mathbb{R}$, then system (1)–(3) represents a classical power system model with constant demand. We assume below that there exists an equilibrium to this system.

Definition 1: An equilibrium point of system (1)–(3) with $d^c(t) = \mathbf{0}_{|N|}$, $t \in \mathbb{R}$ is a value of the states (η, ω, x^s) for which the time derivatives of the system are equal to zero.

Assumption 1: There exists an equilibrium point $(\eta^*, \omega^*, x^{s,*})$ to system (1)–(3), with $d^c(t) = \mathbf{0}_{|N|}$, $t \in \mathbb{R}$.

It should be noted that the problem of the existence of an equilibrium point to (1)–(3) with $d^c(t) = \mathbf{0}_{|N|}$ is a problem that has been studied in the literature (e.g., see [22]), and sufficient conditions involving large enough line susceptances have been derived.

In addition, we impose a constraint on the differences of the phase angles at the equilibrium. This assumption, stated below, is ubiquitous in power network literature, and is treated as a security constraint.

Assumption 2: $|\eta_{ij}^*| < \frac{\pi}{2}$ for all $(i, j) \in E$.

C. Conditions on Generation and Demand Dynamics

In this section, we present the conditions for the system in (3). In particular, we make the following assumptions.

Assumption 3: For each $j \in N$, the system $\dot{x}_j^s = f_j(x_j^s, 0)$ has no compact invariant set other than equilibrium points.

Assumption 3 implies that when the frequency deviation in (3) is zero, then any compact invariant set of (3) consists of equilibrium points only. For a stable linear system, the latter means that the state matrix has no eigenvalues on the imaginary axis except from a possible single eigenvalue at the origin.

Furthermore, the following assumption ensures that at equilibrium, the frequency will be at its nominal value.

Assumption 4: There exists at least one bus j such that when the vector field in (3) satisfies $f_j(\bar{x}_j^s, -\bar{\omega}_j) = 0$, for some constants $\bar{\omega}_j$ and $\bar{x}_j^s$, then $\bar{\omega}_j = 0$.

Remark 2: Assumption 4 requires that for at least one bus, the dynamics are such that an equilibrium can be reached only if the frequency is at its nominal value. Such requirement is satisfied by control policies where integral action is used and also by more general schemes, as discussed in Section VII. Moreover, note that Assumption 4 needs not be satisfied by all buses. This reflects the fact that secondary control is performed using a small number of buses, where the rest may only provide support at faster timescales without incorporating integral action.

The final condition on the dynamics in (3) is related to a notion of passivity that is discussed next.

Definition 2: System (3) is said to be locally input strictly passive around the constant input $-\bar{\omega}_j$ and the point $\bar{x}_j^s$ if there exist open neighborhoods Ω_j of $-\bar{\omega}_j$ and X_j^s of $\bar{x}_j^s$ and a continuously differentiable positive semidefinite function $V_j^S(x_j^s)$ (called the storage function), such that for all $-\omega_j \in \Omega_j$ and all $x_j^s \in X_j^s$, one has

$$\dot{V}_j^S(x_j^s) \leq (-\omega_j + \bar{\omega}_j)(s_j - \bar{s}_j) - \phi_j(-\omega_j + \bar{\omega}_j), \quad (4)$$

where ϕ_j is a positive definite function and $\bar{s}_j = g_j(\bar{x}_j^s, -\bar{\omega}_j)$.

We now consider an equilibrium point of (3) with frequency³ $\omega_j^* = 0$ and equilibrium states $x_j^{s,*}$, $j \in N$ and suppose that the power supply variables at each bus satisfy the input strict passivity condition around this point.

Assumption 5: For each $j \in N$, the dynamics (3) are locally input strictly passive around the constant input $-\omega_j^* = 0$ and the equilibrium state $x_j^{s,*}$, in the sense of Definition 2, with storage function $V_j^S(x_j^s)$ having a strict minimum at $x_j^s = x_j^{s,*}$.

Remark 3: Assumption 5 is a decentralized condition on the continuous power supply dynamics that holds for many dynamical systems considered in the literature and allows the inclusion of higher order schemes (see also [9] and the discussion within it). In Section VII, we provide various relevant examples that satisfy Assumption 5 to demonstrate its practicality within the considered secondary frequency control setting.

V. ON-OFF LOADS

A. Problem Formulation

In this section, we consider frequency-dependent on–off loads that respond to frequency deviations by switching to an appropriate state in order to aid the network at urgencies. As the network returns to its normal operating conditions, the loads return to their initial states as well, hence affecting users' comfort

³As discussed later within this paper, it easily follows from Assumption 4 that the equilibrium frequency always satisfies $\omega_j^* = 0 \quad \forall j \in N$.

Fig. 1. On-off controllable demand deviations as described in (5).

for short periods only. In particular, for each $j \in N$, we let the controllable demand deviations d_j^c be given by the discontinuous map $f_j^c : \mathbb{R} \rightarrow \mathbb{R}$ defined as

$$d_j^c = f_j^c(\omega_j) = \begin{cases} \bar{d}_j, & \omega_j > \bar{\omega}_j \\ 0, & \underline{\omega}_j < \omega_j \leq \bar{\omega}_j \\ \underline{d}_j, & \omega_j \leq \underline{\omega}_j \end{cases} \quad (5)$$

where $-\infty < \underline{d}_j \leq 0 \leq \bar{d}_j < +\infty$, and $\bar{\omega}_j > 0 > \underline{\omega}_j$. The map (5) is depicted in Fig. 1. Note that (5) can be trivially extended to include more discrete values that would possibly respond to higher frequency deviations and could correspond to various controllable loads within a bus with dissimilar switching thresholds. The extension of our results to such cases is trivial and is omitted for simplicity.

To cope with the discontinuous nature of the loads and to have well-defined solutions to system (1)–(3), (5) for all time, a common approach is to relax (5) at the points of discontinuity with a corresponding map, known as the Filippov set valued map [23]. In particular, this takes the following form:

$$F[d_j^c] = \begin{cases} [0, \bar{d}_j], & \omega_j = \bar{\omega}_j \\ [\underline{d}_j, 0], & \omega_j = \underline{\omega}_j, \quad j \in N. \\ \{f_j^c(\omega_j)\}, & \text{otherwise.} \end{cases} \quad (6)$$

The state of the interconnected system (1)–(3), (5) is denoted by $x = (\eta, \omega, x^s) \in \mathbb{R}^n$, $n = |E| + |N| + \sum_{j \in N} n_j$, where any variable without subscript represents a vector with all respective components. By replacing d_j^c in (1) with (6), we obtain the following system representation:

$$\dot{x} \in Q(x) \quad (7)$$

where Q is a set valued map given by

$$Q(x) = \begin{cases} \{\omega_i - \omega_j\}, (i, j) \in E \\ \left\{ \frac{1}{M_j}(-p_j^L + s_j - v_j - \sum_{k: j \rightarrow k} p_{jk} + \sum_{i: i \rightarrow j} p_{ij}) : v_j \in F[d_j^c] \right\}, j \in N \\ \{f_j^s(x_j^s, -\omega_j)\}, j \in N. \end{cases}$$

Remark 4: For the analysis of system (1)–(3), (5) we will be considering its Filippov solutions. In particular, a Filippov

solution of (1)–(3), (5) on an interval $[0, t_1]$ is an absolutely continuous map $x(t)$, $x : [0, t_1] \rightarrow \mathbb{R}^n$ that satisfies (7) for almost all $t \in [0, t_1]$. These are often used to overcome the complications associated with the discontinuity⁴ of the vector field. Krasovskii solutions [16, Definition 4.2] are also frequently used for the study of discontinuous systems. It should be noted that for system (1)–(3), (5), Filippov and Krasovskii solutions are equivalent⁵ [25].

B. Equilibria and Existence of Solutions

First, we investigate the existence of Filippov solutions of system (1)–(3), (5), and then we study its equilibria. The existence of Filippov solutions is established using the following lemma.

Lemma 1: There exist Filippov solutions of system (1)–(3), (5) starting from any initial condition $x_0 \in \mathbb{R}^n$.

Proof: The Lemma follows from [23, Proposition 3]. This states that solutions exist if Q is locally essentially bounded. The latter follows from the boundedness of the step size of the discontinuities in (5) and the Lipschitz property of the rest of the dynamics. ■

An equilibrium of (7) is defined as follows.

Definition 3: The point $x^* = (\eta^*, \omega^*, x^{s,*})$ defines an equilibrium of system (7) if $0_n \in Q(x^*)$.

A Lyapunov stable equilibrium point is defined as follows.

Definition 4: An equilibrium point x^* of (7) is Lyapunov stable if for all $\epsilon > 0$ there exists a $\delta > 0$ s.t. any Filippov solution $x(t)$ of (1)–(3), (5) with initial condition $x(0) = x_0$, $\|x_0 - x^*\| < \delta$, satisfies $\|x(t) - x^*\| < \epsilon$ for all $t \geq 0$.

At an equilibrium of the system, the controllable demand takes its value from a set that depends on ω_j^* , i.e., $d_j^{c,*} \in F[d_j^c](\omega_j^*)$, $j \in N$. Lemma 2 below shows that this set is singleton, namely, $Q(x^*) = \{0_n\}$ and $\omega^* = 0_{|N|} = d^{c,*}$.

Lemma 2: Let Assumptions 1 and 4 hold. Then, there exists an equilibrium point $x^* = (\eta^*, \omega^*, x^{s,*})$ of (7). Furthermore, for any equilibrium point of (7), we have $\omega^* = 0_{|N|}$ and $Q(x^*) = \{0_n\}$.

Proof: When Assumptions 1 and 4 hold, then there exists an equilibrium to system (1)–(3) with $d^c(t) = 0_{|N|}$, $t \in \mathbb{R}$ that satisfies $\omega^* = 0_{|N|}$. From (5), $\omega^* = 0_{|N|}$ implies $d^{c,*} = 0_{|N|}$, and hence the equilibrium of (1)–(3) with $d^c(t) = 0_{|N|}$, $t \in \mathbb{R}$ is also an equilibrium to (7). From (1a) and Assumption 4, it also follows that any equilibrium of (7) satisfies $\omega^* = 0_{|N|}$, which implies $Q(x^*) = \{0_n\}$ from (6). ■

C. Convergence Analysis

We now state the main result of this section. Its proof is provided in the Appendix.

⁴The word switching is sometimes used within this paper to refer to the transition of the loads between the on and off states. It should be noted, although, that system (1)–(3), (5) is not a switching system as described in, e.g., [24], but it is rather a continuous system with a discontinuous right-hand side.

⁵That is, a Krasovskii solution is also a Filippov solution, and a Filippov solution is also a Krasovskii solution.

Theorem 1: Let Assumptions 1, 3, and 4 hold, and consider an equilibrium x^* where Assumptions 2 and 5 hold. Then, x^* is Lyapunov stable. Furthermore, there exists a compact neighborhood of this equilibrium such that Filippov solutions $x = (\eta, \omega, x^s), x : [0, \infty) \rightarrow \mathbb{R}^n$ of system (1)–(3), (5) starting in this neighborhood converge to the set of equilibria of the system that lies in this neighborhood. In particular, the frequency vector ω converges to $\omega^* = \mathbf{0}_{|N|}$.

Theorem 1 states that the solutions that start sufficiently close to x^* are guaranteed to converge to the set of equilibrium points, which suggests by Lemma 2 that the frequency is restored to its nominal value after transient load-side participation. Note that Theorem 1 concludes convergence to a set of equilibria rather than a single equilibrium point (see also Remark 9 after the proof of the theorem). It should also be noted that the local nature of the convergence result in Theorem 1 is due to the nonlinearity of the sinusoids in the power transfer (1c), and the fact that the passivity assumption on the generation dynamics (Assumption 5) holds locally.⁶

D. Chattering

A possible feature of discontinuous systems is the occurrence of infinitely many transitions within some finite time, a phenomenon known as chattering; see, e.g., [26]. Such behavior is often undesirable and impedes practical implementations.

In our setting, chattering may occur in on–off loads, as shown numerically in Section VIII. The reason such behavior may occur is that the frequency derivative may change sign when passing a discontinuity, causing the vector field to point toward the discontinuity. For instance, suppose that $0 < M_j \dot{\omega}_j(t_1) < \bar{d}_j$ for some time instant $t_1 > 0$, and that the threshold $\bar{\omega}_j$ is met at this time. Then, the load d_j^c switches on, causing a sign change in the value of $\dot{\omega}_j$. Hence, the frequency vector field will point at a direction of frequency decrease that will force the load to switch off. These on/off switches occur infinitely many times in finite time, resulting in the aforementioned chattering behavior. Note that this phenomenon is only observed here during the transient response of the loads, as the mechanical power injection will eventually dictate the sign of the vector field and regulate the frequency to its nominal value, as shown in Theorem 1.

VI. HYSTERESIS ON CONTROLLABLE LOADS

A. Problem Formulation

In this section, we propose the use of hysteretic dynamics in on–off controllable loads, which means that a controllable load switches on and off at different frequency thresholds. As it will be shown, this modification will ensure that the system does not exhibit chattering. For relevant applications of hysteric dynamics in ruling out chattering and other undesired features, see, e.g., [26]–[29].

⁶In particular, if the sinusoids were linearized and the passivity property on the generation dynamics was global, then a set of equilibrium points of the resulting dynamical system would have been globally attractive.

Fig. 2. Hysteresis dynamics for controllable loads as described in (8).

We consider hysteretic dynamics for controllable loads that satisfy

$$d_j^c = \bar{d}_j \sigma_j \quad (8a)$$

$$\sigma_j(t^+) = \begin{cases} \text{sgn}(\omega_j), & |\omega_j| > \omega_j^1 \\ 0, & |\omega_j| < \omega_j^0 \\ \sigma_j(t), & \omega_j^0 < |\omega_j| < \omega_j^1 \end{cases} \quad (8b)$$

where $j \in N$, $t^+ = \lim_{\epsilon \rightarrow 0} (t + \epsilon)$, and the frequency thresholds ω_j^0 and ω_j^1 satisfy $\omega_j^1 > \omega_j^0 > 0$. Note that σ_j takes its value from the set $P = \{-1, 0, 1\}$. A schematic of the hysteretic dynamics is shown in Fig. 2.

In the remainder of this section and in the next section, we provide a detailed definition of the overall dynamical system as a hybrid system [16] and use the corresponding tools for its analysis.

In particular, system (1)–(3), with hysteretic controllable loads as in (8), can be described by the states $z = (x, \sigma)$, where $x = (\eta, \omega, x^s) \in \mathbb{R}^n$ is the continuous state and $\sigma \in P^{|N|}$ the discrete state. We also denote by Λ the domain where the state z takes values, which is a subset of $\mathbb{R}^n \times P^{|N|}$, where for each ω_j the value of σ_j satisfies $\sigma_j \in \mathcal{I}_j(\omega_j)$, where

$$\mathcal{I}_j(\omega_j) = \begin{cases} \{\text{sgn}(\omega_j)\}, & |\omega_j| > \omega_j^1, \\ \{0\}, & |\omega_j| < \omega_j^0, \\ \{0, \text{sgn}(\omega_j)\}, & \omega_j^0 \leq |\omega_j| \leq \omega_j^1. \end{cases}$$

This restriction on the state space ensures that the initial conditions for σ are compatible with their right-hand limits in (8b) and is made to simplify the presentation of the subsequent analysis and results.

The continuous part of the dynamics is given by

$$\dot{\eta}_{ij} = \omega_i - \omega_j, \quad (i, j) \in E, \quad (9a)$$

$$M_j \dot{\omega}_j = -p_j^L + s_j - (\bar{d}_j \sigma_j) - \sum_{k:j \rightarrow k} p_{jk} + \sum_{i:i \rightarrow j} p_{ij}, \quad j \in N, \quad (9b)$$

$$\dot{x}_j^s = f_j(x_j^s, -\omega_j), \quad j \in N, \quad (9c)$$

$$\dot{\sigma}_j = 0, \quad j \in N, \quad (9d)$$

where p_{ij} and s_j are given by (1c) and (3), respectively. This is valid when z belongs to the set

$$C = \Lambda = \{z \in \mathbb{R}^n \times P^{[N]} : \sigma_j \in \mathcal{I}_j(\omega_j), \quad \forall j \in N\}. \quad (10)$$

Alternatively, when z belongs to the set D defined as

$$D = \{z \in \Lambda : |\omega_j| \in \{\omega_j^0, \omega_j^1\}, \sigma_j \in \mathcal{I}_j^D(\omega_j), \quad \forall j \in N\} \quad (11)$$

with

$$\mathcal{I}_j^D(\omega_j) = \begin{cases} \{0\}, & |\omega_j| = \omega_j^1, \\ \{\text{sgn}(\omega_j)\}, & |\omega_j| = \omega_j^0, \end{cases}$$

the system dynamics evolve according to the following discrete update rule:

$$x^+ = x \quad (12a)$$

$$\sigma_j(t^+) = \begin{cases} \text{sgn}(\omega_j), & |\omega_j| = \omega_j^1 \\ 0, & |\omega_j| = \omega_j^0. \end{cases} \quad (12b)$$

We can now provide the following compact representation for the hybrid system (1)–(3), (8):

$$\dot{z} = f(z), \quad z \in C \quad (13a)$$

$$z^+ = g(z), \quad z \in D \quad (13b)$$

where the maps $f(z) : C \rightarrow \Lambda$ and $g(z) : D \rightarrow C$ are given by (9) and (12), respectively; the sets C and D by (10) and (11), respectively; and $z^+ = z(t^+)$. Note that $z^+ = g(z)$ represents a discrete dynamical system where z^+ is determined by the current value of the state z and the update rule given by g .

B. Analysis of Equilibria and Solutions

Before investigating the stability of the hybrid system in (13), we characterize its equilibria and establish the existence and completeness of solutions.

Note that we call a point $z^* = (x^*, \sigma^*)$ an equilibrium of (13) if $f(z^*) = 0$ when $z^* \in C$, and $z^* = g(z^*)$ when $z^* \in D$. Now, we state the following lemma.

Lemma 3: Let Assumptions 1 and 4 hold. Then, there exists an equilibrium of (13). Furthermore, for any equilibrium point $z^* = (x^*, \sigma^*)$ of (13), we have $\omega^* = \sigma^* = \mathbf{0}_{|N|}$. Moreover, $z^* \in C$.

Proof: The existence of an equilibrium of (13) follows analogously with the proof of Lemma 2. Recall that any equilibrium z^* of (13) satisfies $f(z^*) = 0$ when $z^* \in C$, and $z^* = g(z^*)$ when $z^* \in D$. Since $g(z) : D \rightarrow C$, it therefore follows that $z^* \in C$. From Assumption 4 and (1a) and (1c) at equilibrium, it follows that $\omega^* = \mathbf{0}_{|N|}$, which implies that $\sigma^* = \mathbf{0}_{|N|}$.

Following [16], we provide a definition of a hybrid time domain, hybrid solution, and complete and maximal solutions for the systems described by (13).

Definition 5: (See [16]) A subset of $\mathbb{R}_{\geq 0} \times \mathbb{N}_0$ is a hybrid time domain if it is a union of a finite or infinite sequence of intervals $[t_\ell, t_{\ell+1}] \times \{\ell\}$, with the last interval (if existent) possibly of the form $[t_\ell, t_{\ell+1}] \times \{\ell\}$, $[t_\ell, t_{\ell+1}] \times \{\ell\}$, or $[t_\ell, \infty) \times \{\ell\}$. Consider a function $z(t, \ell) : K \rightarrow \mathbb{R}^n$ defined on a hybrid time domain K such that for every fixed $\ell \in \mathbb{N}$, $t \mapsto z(t, \ell)$ is locally absolutely continuous on the interval $T_\ell = \{t : (t, \ell) \in$

$K\}$. The function $z(t, \ell)$ is a solution to the hybrid system $\mathcal{H} = (C, f, D, g)$ if $z(0, 0) \in C \cup D$ for all $\ell \in \mathbb{N}$ such that T_ℓ has nonempty interior (denoted by $\text{int}T_\ell$). One has

$$z(t, \ell) \in C, \quad \text{for all } t \in \text{int}T_\ell$$

$$\dot{z}(t, \ell) \in f(z(t, \ell)), \quad \text{for almost all } t \in T_\ell$$

$$\text{and for all } (t, \ell) \in K \text{ such that } (t, \ell + 1) \in K$$

$$z(t, \ell) \in D, \quad z(t, \ell + 1) \in g(z(t, \ell)).$$

A solution $z(t, \ell)$ is complete if K is unbounded. A solution z is maximal if there does not exist another solution $\tilde{z}$ with time domain $\tilde{K}$ such that K is a proper subset of $\tilde{K}$ and $z(t, j) = \tilde{z}(t, j)$ for all $(t, j) \in K$.

For convenience in the presentation, we will refer to maximal solutions by just solutions. The existence of complete solutions to (13) are established in the following lemma.

Lemma 4: There exists a complete solution $z = (x, \sigma)$ to (13), starting from any initial condition $z(0, 0) \in \Lambda$.

Furthermore, the following proposition shows the existence of some finite dwell time between switches of states σ_j for any bounded solution. Within it, we denote the time instants where the value of σ_j changes by $t_{\ell,j}, \ell \in \mathbb{N}_0, j \in N$.

Proposition 1: For any complete bounded solution of (13), there exists $\tau > 0$ such that $\min_{\ell \geq 1} (t_{\ell+1,j} - t_{\ell,j}) \geq \tau$ for any $j \in N$.

Remark 5: The importance of Proposition 1 is that it shows that no chattering will occur for any complete bounded solution of system (13). This is because for any finite-time interval τ , the vector σ changes at most $|N|$ times. This highlights the practical advantage of (13) compared to (7). This analytic result is verified using numerical simulations in a realistic power network, as discussed in Section VIII.

C. Stability of Hysteresis System

Now, we are at the position to state the stability result concerning system (13).

Theorem 2: Let Assumptions 1, 3, and 4 hold and consider an equilibrium $z^* = (x^*, \sigma^*)$ of (13), for which Assumptions 2 and 5 hold. Then, there exists a compact neighborhood of x^* such that solutions $z = (x, \sigma)$, with $x(0)$ in this neighborhood and $\sigma(0) \in \mathcal{I}(\omega(0))$, asymptotically converge to the set of equilibria of (13), whose continuous state lies in this neighborhood. In particular, the vectors ω and σ converge to the vector $\mathbf{0}_{|N|}$.

Remark 6: Theorem 2 shows that the hysteretic dynamics in (8) do not compromise the stability of the system. This, together with the absence of chattering shown in Proposition 1, promotes the use of hysteretic dynamics as a means to provide practical and nondisruptive on–off load-side control to the power network.

Remark 7: Although the controllable loads are at their nominal value at equilibrium, they provide ancillary services to the network and improve the performance in transient time. This is numerically investigated in Section VIII. To clarify, note that the convergence region in Theorem 2 is not restricted by the switches but rather by the nonlinearity of the frequency dynamics.

Remark 8: We note that no assumption is made on the graph (G, E) except that it is connected. Therefore, all the results presented in the current and previous sections are applicable on arbitrarily connected graph topologies.

VII. DISCUSSION

It was shown in Section VI that hysteretic on-off loads can be incorporated in an arbitrary network without compromising stability if the continuous, and potentially higher order, supply dynamics satisfy the conditions described in Section IV-A. In this section, we demonstrate the generality and applicability of these conditions by discussing various examples that fit within the proposed framework.

An important feature of our analysis is that it allows to consider a general class of dynamics where the power supply dynamics are described by the summation of a damping term and the series interconnection of a PI controller with an asymptotically stable general linear system, potentially of higher order. The transfer function from $-\omega_j$ to s_j of such a system is given by $S_j(s) = (\frac{K_j}{s} + \tilde{K}_j)G_j(s) + D_j$, where K_j , $\tilde{K}_j$, and D_j are positive constants and $G_j(s)$ a transfer function with no unstable poles. Assumption 4 and the assumptions on (3) are clearly satisfied for this system. Moreover, Assumption 5 is satisfied if there exists $\epsilon_j > 0$ such that the perturbed transfer function $S_j(s) - \epsilon_j$ is positive real. This can be verified numerically using appropriate linear matrix inequality conditions [30, Lemma 6.2], i.e., a computationally efficient convex feasibility problem, or graphically by examining the Nyquist plot of $S_j(j\omega)$, which needs to lie within the open right half plane.

First, we consider power supply dynamics where the output response follows from a PI control scheme acting on a frequency input with a lag. Such dynamics can be described by

$$\dot{\alpha}_j = -K_j\omega_j, \quad \tau_{\beta,j}\dot{\beta}_j = -\beta_j + \alpha_j - \tilde{K}_j\omega_j \quad (14a)$$

$$s_j = \beta_j - D_j\omega_j \quad (14b)$$

where α_j and β_j are the states of the power supply variables and K_j , $\tilde{K}_j$, $\tau_{\beta,j}$, and D_j the positive constants describing the integrator and droop gains, the time constant associated with power generation, and the frequency damping respectively. For (14), it can be shown that Assumption 5 is satisfied if $K_j\tau_{\beta,j} < D_j + \tilde{K}_j$. Furthermore, Assumption 4 is trivially satisfied.

An important aspect of our analysis lies in its ability to consider higher order schemes. A significant example of this can be seen in second-order generation dynamics, often considered to describe turbine-governor behavior (e.g., see [20]). Below, we consider the series interconnection of an integrator and a second-order system with frequency damping, described by

$$\dot{\alpha}_j = -K_j\omega_j, \quad \tau_{\beta,j}\dot{\beta}_j = -\beta_j + \alpha_j \quad (15a)$$

$$\tau_{\gamma,j}\dot{\gamma}_j = -\gamma_j + \beta_j, \quad s_j = \gamma_j - D_j\omega_j \quad (15b)$$

where α_j , β_j , and γ_j are the internal states of the system and K_j , $\tau_{\beta,j}$, $\tau_{\gamma,j}$, and D_j positive constants. It is straightforward to

⁷We assume that no zero/pole cancellation occurs between $G_j(s)$ and the PI controller.

Fig. 3. Nyquist plots of the systems from ω_j to s_j described in (14) and (15), illustrated by blue and red lines, respectively, when the gain conditions stated are marginally satisfied. The passivity of both schemes is implied by the fact that both the plots lie on the right half plane.

deduce that such system satisfies Assumption 4. Furthermore, it can be shown that (15) satisfies Assumption 5 when $K_j(\tau_{\beta,j} + \tau_{\gamma,j}) < D_j$.

The Nyquist plots of the dynamics in (14)–(15) are illustrated in Fig. 3, which depicts the plots of these schemes when the suggested gain conditions are marginally satisfied. Fig. 3 demonstrates the passivity of the considered dynamics when the gain conditions are satisfied, since the Nyquist plots are in the right half plane.

Furthermore, our framework allows to incorporate various realistic dynamical schemes that satisfy Assumption 5 but not Assumption 4. This is relevant since Assumption 4 only needs to be satisfied by at least one bus in the network, as mentioned in Remark 2. To demonstrate an important example of such a case, we consider the fifth-order dynamics used by the Power System Toolbox [31] to describe turbine-governor behavior within the NPCC network. In this model, power supply $\hat{s}_j$ is related to the negative frequency deviation $-\hat{\omega}_j$ in the Laplace domain via the following transfer function:

$$G_j(s) = K_j \frac{1}{(1 + sT_{s,j})} \frac{(1 + sT_{3,j})}{(1 + sT_{c,j})} \frac{(1 + sT_{4,j})}{(1 + sT_{5,j})} + D_j$$

where $T_{s,j}$, $T_{3,j}$, $T_{c,j}$, $T_{4,j}$, and $T_{5,j}$ are time-constants and K_j and D_j the droop and damping coefficients, respectively. Realistic values for these systems are provided by the Power System Toolbox, and it can be shown that Assumption 5 is satisfied by 20 out of the 22 buses with turbine-governor dynamics. Furthermore, for the remaining 2 buses, Assumption 5 is satisfied if the damping coefficients are increased by 28% and 37%, respectively. This demonstrates that the passivity conditions are satisfied by the existing implementations. Note that further examples of schemes that satisfy Assumption 5, including static nonlinearities, first and second order systems, are provided in [9].

VIII. SIMULATION ON THE NPCC 140-BUS SYSTEM

In this section, we verify our analytic results using a numerical simulation on the NPCC 140-bus interconnection system, using the Power System Toolbox [31]. This model is more detailed and realistic than our analytical one, including line resistances, a

Fig. 4. Frequency at Bus 99 with controllable load dynamics as in the following two cases: (i) switching case, and (ii) hysteresis case.

DC12 exciter model, a subtransient reactance generator model, and turbine-governor dynamics.⁸

The test system consists of 93 load buses serving different types of loads including constant active and reactive loads and 47 generation buses. The overall system has a total real power of 28.55 GW. For our simulation, we added three uncontrollable loads on Units 8, 9, and 17, each having a step increase of magnitude 2 p.u. (base 100 MVA) at $t = 1$ s.

Controllable demand was considered within the simulations, with controllable loads controlled every 10 ms. Secondary control was performed from the generation side, where the dynamics satisfied the conditions presented in Section IV-A.

The system was tested for two different cases. In Case (i), on–off controllable loads with dynamics as in (5) were included on 20 load buses. The values for $\bar{\omega}_j$ were selected from a uniform distribution within the range $[0.02 \ 0.07]$ and those of ω_j by $\omega_j = -\bar{\omega}_j$. Controllable loads were also included on 20 load buses for Case (ii), but with dynamics described by (8). To have a fair comparison, the same frequency thresholds were used for both the cases, with $\omega_j^1 = \bar{\omega}_j$ and $\omega_j^0 = 0.15\bar{\omega}_j$. Also, $\bar{d} = -\underline{d} = 0.25$ p.u. was used for both the cases. Furthermore, in order to account for any potential effect of the reactive-power deviations in the response of the network, on–off loads were assumed to induce a reactive-power effect of magnitude 0.25 p.u., i.e., assumed a power factor of about 0.7, which is, in most cases, an underestimate. Cases (i) and (ii) will be referred to as the “switching” and “hysteresis” cases, respectively.

The frequency at Bus 99 for the two tested cases is shown in Fig. 4, where it can be seen that the frequency returns to its nominal value for both the cases, as suggested in Theorems 1 and 2. Moreover, Fig. 5 demonstrates that the inclusion of on–off loads decreases the maximum overshoot in frequency, by comparing the largest deviation in frequency with and without the on–off controllable loads at Buses 1 – 40, where frequency overshoot was seen to be the largest. From Fig. 5, it can be seen that the largest frequency overshoot has dropped from about 0.28 to about 0.18 Hz, demonstrating a drop of more than 30%. Note

Fig. 5. Largest frequency overshoot for Buses 1–40 for three cases: (a) use of switching loads, (b) use of hysteresis loads, and (c) no use of controllable loads. Note that the graphs for Cases (i) and (ii) are almost identical in the figure.

Fig. 6. Controllable demand at four buses with switching on–off loads. All the loads stay switched off after 15 s.

that the similar responses from switching and hysteretic loads in Fig. 5 follow from the fact that identical frequency thresholds have been chosen. Furthermore, the simulation results demonstrated that the deviations in voltage magnitude have always been within 3.3% of the nominal value at all times, justifying the constant voltages assumption in Section III.

Fig. 6 shows controllable demand at four buses for Case (i), depicting very fast switches, indicated by the thick blue lines, which demonstrates chattering behavior.⁹ In contrast, when Case (ii) is considered, such fast switching in loads is not observed on those four buses, as exhibited in Fig. 7. Furthermore, it was seen within the simulations that all the loads switched off after 30 s, which demonstrates the nondisruptive nature of the two schemes, since loads return to their nominal demand after a brief period. It should be noted that switching loads demonstrated a faster restoration than that demonstrated by hybrid ones as a result of their higher switch-off thresholds. Thus, this numerical investigation supports the analysis of

⁸The details of the simulation models can be found in the Power System Toolbox data file datanp48.

⁹Note that in practice loads will not be able to switch arbitrarily fast, since their physical parameters will impose some time delays between switches. However, very fast switching will still be observed, which is an undesirable feature.

Fig. 7. Controllable demand at four buses with hysteresis on–off loads. All the loads stay switched off after 30 s.

this paper, verifying that frequency-dependent on–off loads are able to provide ancillary service in the power network and that hysteresis eliminates any chattering behavior.

IX. CONCLUSION

We have considered the problem of secondary frequency control in power networks where controllable on–off loads provided ancillary services. We first considered a general class of continuous dynamics together with loads that switch on when some frequency threshold is reached and switch off otherwise. Stability guarantees were provided for this framework. Furthermore, it was discussed that such on–off schemes might exhibit arbitrarily fast switching, which might limit their practicality. To cope with this issue, on–off loads with hysteretic dynamics were considered. It was shown that such loads do not exhibit chattering and that their inclusion does not compromise power network stability. Hence, such schemes are usable for practical implementations. Both the schemes ensure that controllable loads return to their nominal behavior at equilibrium and, hence, that disruptions occur for brief periods only. We discussed that our analysis allows the incorporation of on–off loads together with a broad range of continuous dynamics, including various highly relevant and practical schemes, which highlights the applicability of our results. Numerical simulations on the NPCC 140-bus system verified our main findings, demonstrating that the presence of on–off loads reduces the frequency overshoot and that hysteresis schemes resolve issues caused by chattering. Interesting potential extensions in the analysis include incorporating frequency-dependent on–off loads within the primary frequency control timeframe, more advanced load dynamics, and models that take into account voltage dynamics.

APPENDIX PROOFS OF RESULTS

Within the proofs of Lemma 2 and Theorem 1, we will make use of the following equilibrium equations for system (1)–(3), which follow from Definition 3 and Lemma 2. Below, we let $\bar{N} \subseteq N$ be the set of all the buses that satisfy the condition in Assumption 4, i.e., those that satisfy $f_j(\bar{x}_j^s, -\bar{\omega}_j) = 0$ only

when $\bar{\omega}_j = 0$.

$$0 = \omega_j^* - \omega_j^*, (i, j) \in E \quad (16a)$$

$$0 = -p_j^L + s_j^* - \sum_{k:j \rightarrow k} p_{jk}^* + \sum_{i:i \rightarrow j} p_{ij}^*, j \in N \quad (16b)$$

$$p_{ij}^* = B_{ij} \sin \eta_{ij}^*, (i, j) \in E \quad (16c)$$

$$0 = \omega_j^*, j \in \bar{N} \quad (16d)$$

$$0 = d_j^{c,*}, j \in N. \quad (16e)$$

Proof of Theorem 1: To prove Theorem 1, we will make use of [32, Th. 3]. First, note that the set valued map Q in (7) is upper semicontinuous¹⁰ and takes compact, convex values. For the dynamics (1)–(3), and (5), we define

$$\bar{V}(\eta, \omega) = V_F(\omega) + V_P(\eta) \quad (17)$$

where $V_F(\omega) = \frac{1}{2} \sum_{j \in N} M_j \omega_j^2$, and $V_P(\eta) = \sum_{(i,j) \in E} B_{ij} \int_{\eta_{ij}^*}^{\eta_{ij}} (\sin \phi - \sin \eta_{ij}^*) d\phi$.

By substituting (1a) and (1b) for $\dot{\eta}_{ij}$ and $\dot{\omega}_j$ and using the differential inclusion for d_j^c for $j \in N$, the set-valued time-derivative of $\bar{V}$ along the solutions of (7) is then obtained as

$$\begin{aligned} \dot{\bar{V}} = & \left\{ \sum_{j \in N} \omega_j (-p_j^L + p_j^M - v_j - d_j^u - \sum_{k:j \rightarrow k} p_{jk} + \sum_{i:i \rightarrow j} p_{ij}) \right. \\ & + \sum_{(i,j) \in E} B_{ij} (\sin \eta_{ij} - \sin \eta_{ij}^*) \\ & \left. \times (\omega_i - \omega_j) : v_j \in F[d_j^c(\omega_j)] \right\}. \end{aligned} \quad (18)$$

Furthermore, from Assumption 5, it follows that within neighborhoods Ω_j and X_j^s of $-\omega_j^*$ and $x_j^{s,*}$, respectively, it holds that

$$\dot{V}_j^S(x_j^s) \leq (-\omega_j)(s_j - s_j^*) - \phi_j(-\omega_j), j \in N \quad (19)$$

noting that $\omega^* = \mathbf{0}_{|N|}$ follows from Lemma 2.

We then consider the following function:

$$V(\eta, \omega, x^s) = \bar{V}(\omega, \eta) + \sum_{j \in N} V_j^S(x_j^s) \quad (20)$$

which, as follows from (17) and Assumption 5, is continuously differentiable with respect to the states and has a local strict minimum at $(\eta^*, \omega^*, x^{s,*})$, as follows from Assumptions 2 and 5, and is hence suitable to be used as a Lyapunov function candidate. Furthermore, it trivially follows that V is regular, following the definition in [32, pp. 363–364].

We now consider the set-valued derivative of V with respect to (7), i.e., $\dot{V}(x) = \left\{ \frac{\partial V}{\partial x} z : z \in Q(x) \right\}$. By substituting (1c) and using (18)–(19), it follows that

$$\dot{V} = \left\{ \sum_{j \in N} (-\omega_j v_j - \phi_j(-\omega_j)) : v_j \in F[d_j^c(\omega_j)] \right\}. \quad (21)$$

¹⁰For the definition of an upper semicontinuous function, see, e.g., [23, p. 49].

Using (6), we conclude that $(\max \dot{V}) \leq -\sum_{j \in N} \phi_j(-\omega_j) \leq 0$, where the maximum is taken over all the points in the set given by the right-hand side of (21).

From Assumptions 2 and 5, the function V has a strict local minimum at $x^* = (\eta^*, \omega^*, x^{s,*})$. Then, noting that each point in $\dot{V}$ is nonpositive, we can construct a compact set Ξ around the equilibrium point, of the form $\Xi = \{(\eta, \omega, x^s) : V \leq \epsilon, x^* \in \Xi, \Xi \text{ connected}\}$ for some $\epsilon > 0$ sufficiently small, such that $(\eta, \omega, x^s) \in \Xi$ implies that ω_j and x_j^s , respectively, lie in Ω_j and $X_j^s \forall j \in N$, and $\eta_{ij} < \pi/2 \forall (i, j) \in E$. Note that solutions initiated within Ξ remain in Ξ for all future times. Therefore, since Ξ can be selected to be arbitrarily small, it follows that x^* is Lyapunov stable.

[32, Th. 3] is now invoked for the function V on the compact set Ξ along the solutions of (7). First, define the set $Z = \{(\eta, \omega, x^s) : 0 \in \dot{V}\}$ and let M be the largest weakly¹¹ invariant set within $\Xi \cap Z$. Then, [32, Th. 3] guarantees that all the solutions of (1)–(3), (5) with initial conditions $(\eta(0), \omega(0), x^s(0)) \in \Xi$ converge to M as $t \rightarrow \infty$. Note that $0 \in \dot{V}$ only if $\omega = \omega^* = 0_{|N|}$, which also implies that $d^c = 0_{|N|}$. This suggests from (1a) and¹² Assumption 3 that the vectors η and x^s are equal to some constant vectors $\bar{\eta}$ and $\bar{x}^s$, on the invariant set. Therefore, we conclude by [32, Th. 3] that all the Filippov solutions of (1)–(3), (5) with initial conditions $(\eta(0), \omega(0), x^s(0)) \in \Xi$ converge to the set of equilibrium points within Ξ . ■

Remark 9: Theorem 1 shows that all the solutions starting in a neighborhood Ξ of the equilibrium point x^* will converge to the set of equilibrium points within Ξ . Furthermore, Ξ can be chosen arbitrarily small, so x^* is also Lyapunov stable. An extension could be obtained if, in addition to the requirements of Theorem 1, Assumption 5 holds for all the equilibria within Ξ . This means that such equilibria are all Lyapunov stable, and hence arguments analogous to those in [33, Proposition 4.7, Th. 4.20] can be used to deduce¹³ that all solutions starting in Ξ converge to an equilibrium point in Ξ .

Proof of Lemma 4: To show the existence of solutions, first note that for any initial condition, it holds that either $z(0, 0) \in C$ or $z(0, 0) \in D$. The latter results in $z(0, 1) \in C$ as $g(z) : D \rightarrow C$. Then, from the Lipschitz property of the dynamics in (13a), it follows from [16, Proposition 2.10] that a solution to (13) exists. Furthermore, noting that $g : D \rightarrow C$, it follows also from [16, Proposition 2.10] that every solution to (13) is either complete or has a finite number of intervals with the last interval of the form $[t_\ell, t_{\ell+1}) \times \{\ell\}$ with $t_{\ell+1} < \infty$. The latter can be excluded due to the global Lipschitz property of the vector field in (13a). Hence, a complete solution to (13) exists from any initial condition $z(0, 0) \in \Lambda$. ■

Proof of Proposition 1: Consider any bounded solution of system (13) with states $z = (\eta, \omega, x^s, \sigma)$ and define

$\epsilon_j = \omega_j^1 - \omega_j^0$ following the description in (8). For any finite-time interval between two consecutive switches at bus j , i.e., $[t_{\ell,j}, t_{\ell+1,j}]$, the value of $\dot{\omega}_j$ is bounded from above by a constant, say $d\omega_j^{\max}$. The fact that $d\omega_j^{\max}$ is finite follows from the boundedness of the solution and the fact that the vector field in (13a) is globally Lipschitz. Then, it follows that $t_{\ell+1,j} - t_{\ell,j} \geq \epsilon_j / d\omega_j^{\max}$. Then, a uniform bound between consecutive switches at any bus can be provided by $\tau = \min_j \epsilon_j / d\omega_j^{\max}$. Notice that the bound provided in the proposition is stated to hold from the second switching time to include the case $z(0, 0) \in D$. ■

Proof of Theorem 2: For the proof, we shall make use of the continuous function V , described in (20). Using similar arguments as in the proof of Theorem 1 and defining $T_c = \{t : (t, \ell) \in K, z(t, \ell) \in C\}$ and $T_d = \{t : (t, \ell) \in K, z(t, \ell) \in D\}$, where K is a hybrid time domain for (13) and C and D defined by (10) and (11), respectively, it follows that

$$\dot{V} \leq -\sum_{j \in N} \phi_j(-\omega_j), t \in T_c \quad (22a)$$

$$V(g(z)) - V(z) = 0, t \in T_d \quad (22b)$$

along any solution of (13). Note that when $z \in D$, the value of V remains constant, as it only depends on x that is constant from (12).

Note that V is a function of x only and that it has a strict minimum at the equilibrium point, since $\bar{V}(\eta, \omega)$ has a minimum at $(\eta^*, 0)$ from (17), and since $V_j^s(x_j^s)$ have strict local minima at $x_j^{s,*}$ for each $j \in N$ from Assumption 5. Hence, there exists a compact set $S = \{(x, \sigma) : x \in \Xi \text{ and } \sigma \in \mathcal{I}(\omega)\}$ for some neighborhood Ξ of x^* , such that the solutions initiated in S stay in S for all future times. The set Ξ is obtained in the same vein as in the proof of Theorem 1, i.e., $\Xi = \{(\eta, \omega, x^s) : V \leq \epsilon, x^* \in \Xi, \Xi \text{ connected}\}$ for some $\epsilon > 0$ sufficiently small, such that $(\eta, \omega, x^s) \in \Xi$ implies that ω_j and x_j^s lie in Ω_j and X_j^s , respectively, $\forall j \in N$, and $\eta_{ij} < \pi/2 \forall (i, j) \in E$. Note that Ξ is compact, and hence from (22) it follows that all the solutions of (13) that start within Ξ are bounded. Furthermore, from Lemma 4, it follows that all the solutions within Ξ are complete. In order to prove Theorem 2, we make use of [16, Corollary 8.7 (b)], which follows from [16, Th. 8.2]. In particular, this corollary can be used, since from Proposition 1 we have that the time interval between any two consecutive switches is bounded from below by a positive number. From [16, Corollary 8.7 (b)], we deduce that all the complete and bounded solutions within S converge to the largest weakly invariant subset¹⁴ of the set $\{z : V(z) = r\} \cap S \cap u_c^{-1}(0)$, for some $r > 0$, where $u_c^{-1}(0) = \{z \in C : \dot{V} = 0\}$. We now have that if $\dot{V} = 0$, then $\omega = 0$, which implies that $\sigma = 0$ from (8). Hence, using also Assumption 3 and (1a), we deduce that $z = (\eta, \omega, x^s, \sigma)$ converges to the set of equilibrium points in S . Note that the set of equilibria of (13) within S has continuous state x that lies in Ξ . ■

Remark 10: The well posedness of (13), see [16, Th. 6.8], is required to use the invariance principle from [16, Th. 8.2]. The

¹¹We use the notion of weakly invariant set from [32, Definition 4].

¹²Note that the right-hand side of (1)–(3) is Lipschitz within a neighborhood of M , since $\omega = 0_{|N|}$ within M . Hence, M is also an invariant set of (1)–(3).

¹³In particular, the set of equilibrium points in Ξ is the ω -limit set of the trajectories in Ξ . Furthermore, each trajectory $x(t)$ in Ξ has an ω -limit point, since it is bounded; i.e., it has a subsequence $x(t_n)$ that converges to an equilibrium point as $t_n \rightarrow \infty$. Hence, if the equilibrium points in Ξ are Lyapunov stable, one can easily deduce that $x(t)$ also converges to an equilibrium point.

¹⁴We use the notion of weakly invariant sets provided in [16, Definition 6.19].

fact that (13) is well posed follows trivially, since the sets C and D are closed, and the function f is Lipschitz continuous and g is outer semicontinuous¹⁵ and locally bounded relative to D . Note also that sets C and D are closed despite the discontinuity of function $\text{sgn}(\omega_j)$ at $\omega_j = 0$, since in the definitions of $\mathcal{I}_j(\omega_j)$ and $\mathcal{I}_j^D(\omega_j)$, function $\text{sgn}(\omega_j)$ is used for values of ω_j that do not include $\omega = 0$.

REFERENCES

- [1] A. Kasis, N. Monshizadeh, and I. Lestas, "Secondary frequency control with on-off load side participation in power networks," in *Proc. 56th IEEE Conf. Decis. Control*, 2017, pp. 5702–5707.
- [2] H. Lund, "Large-scale integration of optimal combinations of PV, wind and wave power into the electricity supply," *Renewable Energy*, vol. 31, no. 4, pp. 503–515, 2006.
- [3] A. Ipakchi and F. Albuyeh, "Grid of the future," *IEEE Power Energy Mag.*, vol. 7, no. 2, pp. 52–62, Mar.–Apr. 2009.
- [4] P. Kundur, N. J. Balu, and M. G. Lauby, *Power System Stability and Control*, vol. 7. New York, NY, USA: McGraw-Hill, 1994.
- [5] A. Ulbig, T. S. Borsche, and G. Andersson, "Impact of low rotational inertia on power system stability and operation," *IFAC Proc. Volumes*, vol. 47, no. 3, pp. 7290–7297, 2014.
- [6] A. Molina-Garcia, F. Bouffard, and D. S. Kirschen, "Decentralized demand-side contribution to primary frequency control," *IEEE Trans. Power Syst.*, vol. 26, no. 1, pp. 411–419, Feb. 2011.
- [7] S. Trip and C. de Persis, "Optimal generation in structure-preserving power networks with second-order turbine-governor dynamics," in *Proc. IEEE Eur. Control Conf.*, 2016, pp. 916–921.
- [8] C. Zhao, U. Topcu, N. Li, and S. H. Low, "Design and stability of load-side primary frequency control in power systems," *IEEE Trans. Autom. Control*, vol. 59, no. 5, pp. 1177–1189, May 2014.
- [9] A. Kasis, E. Devane, C. Spanias, and I. Lestas, "Primary frequency regulation with load-side participation—Part I: Stability and optimality," *IEEE Trans. Power Syst.*, vol. 32, no. 5, pp. 3505–3518, Sep. 2017.
- [10] E. Devane, A. Kasis, M. Antoniou, and I. Lestas, "Primary frequency regulation with load-side participation—Part II: Beyond passivity approaches," *IEEE Trans. Power Syst.*, vol. 32, no. 5, pp. 3519–3528, Sep. 2017.
- [11] A. Kasis, E. Devane, and I. Lestas, "Primary frequency regulation in power networks with ancillary service from load-side participation," *IFAC-PapersOnLine*, vol. 50, no. 1, pp. 4394–4399, 2017.
- [12] E. Mallada, C. Zhao, and S. Low, "Optimal load-side control for frequency regulation in smart grids," in *Proc. 52nd Annu. Allerton Conf. Commun., Control, Comput.*, 2014, pp. 731–738.
- [13] S. Trip, M. Bürger, and C. de Persis, "An internal model approach to (optimal) frequency regulation in power grids with time-varying voltages," *Automatica*, vol. 64, pp. 240–253, 2016.
- [14] A. Kasis, N. Monshizadeh, E. Devane, and I. Lestas, "Stability and optimality of distributed secondary frequency control schemes in power networks," *IEEE Trans. Smart Grid*, vol. 10, no. 2, pp. 1747–1761, Mar. 2017.
- [15] T. Liu, D. J. Hill, and C. Zhang, "Non-disruptive load-side control for frequency regulation in power systems," *IEEE Trans. Smart Grid*, vol. 7, no. 4, pp. 2142–2153, Jul. 2016.
- [16] R. Goebel, R. G. Sanfelice, and A. R. Teel, *Hybrid Dynamical Systems: Modeling, Stability, and Robustness*. Princeton, U.K.: Princeton Univ. Press, 2012.
- [17] L. Jiang, W. Yao, Q. Wu, J. Wen, and S. Cheng, "Delay-dependent stability for load frequency control with constant and time-varying delays," *IEEE Trans. Power Syst.*, vol. 27, no. 2, pp. 932–941, May 2012.
- [18] M. I. Alomoush, "Load frequency control and automatic generation control using fractional-order controllers," *Elect. Eng.*, vol. 91, no. 7, pp. 357–368, 2010.
- [19] N. Li, C. Zhao, and L. Chen, "Connecting automatic generation control and economic dispatch from an optimization view," *IEEE Trans. Control Netw. Syst.*, vol. 3, no. 3, pp. 254–264, Sep. 2016.
- [20] A. R. Bergen and V. Vittal, *Power Systems Analysis*. Upper Saddle River, NJ, USA: Prentice-Hall, 1999.
- [21] A. Kasis, E. Devane, and I. Lestas, "Stability and optimality of distributed schemes for secondary frequency regulation in power networks," in *Proc. 55th IEEE Conf. Decis. Control*, 2016, pp. 3294–3299.
- [22] F. Dörfler, M. Chertkov, and F. Bullo, "Synchronization in complex oscillator networks and smart grids," *Proc. Nat. Acad. Sci. United States America*, vol. 110, no. 6, pp. 2005–2010, 2013.
- [23] J. Cortes, "Discontinuous dynamical systems," *IEEE Control Syst. Mag.*, vol. 28, no. 3, pp. 36–73, Jun. 2008.
- [24] D. Liberzon, *Switching in Systems and Control*. New York, NY, USA: Springer-Verlag, 2003.
- [25] O. Hájek, "Discontinuous differential equations, i," *J. Differ. Equ.*, vol. 32, no. 2, pp. 171–185, 1979.
- [26] H. Lee and V. I. Utkin, "Chattering suppression methods in sliding mode control systems," *Annu. Rev. Control*, vol. 31, no. 2, pp. 179–188, 2007.
- [27] C. G. Mayhew, R. G. Sanfelice, and A. R. Teel, "Quaternion-based hybrid control for robust global attitude tracking," *IEEE Trans. Autom. Control*, vol. 56, no. 11, pp. 2555–2566, Nov. 2011.
- [28] F. Ceragioli, C. De Persis, and P. Frasca, "Discontinuities and hysteresis in quantized average consensus," *Automatica*, vol. 47, no. 9, pp. 1916–1928, 2011.
- [29] C. Prieur, "Asymptotic controllability and robust asymptotic stabilizability," *SIAM J. Control Optim.*, vol. 43, no. 5, pp. 1888–1912, 2005.
- [30] H. K. Khalil, *Nonlinear Systems*, 3rd ed. Upper Saddle River, NJ, USA: Prentice-Hall, 1996.
- [31] *Power System Toolbox (version 3.0)*, Rensselaer Polytechnic Institute and Cherry Tree Scientific Software, 2009.
- [32] A. Bacciotti and F. Ceragioli, "Stability and stabilization of discontinuous systems and nonsmooth Lyapunov functions," *ESAIM; Control, Optim. Calculus Variations*, vol. 4, pp. 361–376, 1999.
- [33] W. M. Haddad and V. Chellaboina, *Nonlinear Dynamical Systems and Control: A Lyapunov-Based Approach*. Princeton, U.K.: Princeton Univ. Press, 2011.

Andreas Kasis received the B.A. (first class) and M.Eng. (distinction) degrees in information and computer engineering from Robinson College, University of Cambridge, Cambridge, U.K., in 2013 and the Ph.D. degree from the University of Cambridge, in 2017.

He is currently a Research Associate with the Control Group, University of Cambridge. His research interests focus on network analysis, and control and optimization with applications on electrical power networks.

Nima Monshizadeh received the B.Sc. and M.Sc. degrees from the University of Tehran, Tehran, Iran, in 2007 and 2009, respectively, and the Ph.D. degree with honors (cum laude) from the Johann Bernoulli Institute for Mathematics and Computer Science, University of Groningen, Groningen, The Netherlands, in December 2013.

Afterward, he was appointed a Postdoctoral Researcher at the Engineering and Technology Institute, University of Groningen. He was a Research Associate with the Control Group, University of Cambridge, Cambridge, U.K., before taking a tenure track position with the University of Groningen in January 2018. His research interests include power networks, model reduction, and optimization and control of complex networks.

Ioannis Lestas received the B.A. (starred first) and M.Eng. (distinction) degrees in electrical engineering and information sciences and the Ph.D. degree in control theory from the University of Cambridge (Trinity College), Cambridge, U.K., in 2002 and 2007, respectively. His doctoral work was performed as a Gates Scholar.

He was then elected a Junior Research Fellow of Clare College, University of Cambridge and was awarded a five-year Royal Academy of Engineering research fellowship. He is also the recipient of a five-year ERC starting grant. He is currently a University Lecturer with the Department of Engineering, University of Cambridge. His research interests include analysis and control of large-scale networks with applications in power systems and smart grids, data networks, multiagent systems, and biological networks.

¹⁵The definition of an outer semicontinuous function is provided in [16, Definition 5.9].