University of Groningen

Hamiltonian realizations of nonlinear adjoint operators

Fujimoto, Kenji; Scherpen, Jacquélien M.A.; Gray, W. Steven

Published in:
Automatica

DOI:
[10.1016/S0005-1098\(02\)00079-1](https://doi.org/10.1016/S0005-1098(02)00079-1)

IMPORTANT NOTE: You are advised to consult the publisher's version (publisher's PDF) if you wish to cite from it. Please check the document version below.

Document Version
Publisher's PDF, also known as Version of record

Publication date:
2002

[Link to publication in University of Groningen/UMCG research database](#)

Citation for published version (APA):

Fujimoto, K., Scherpen, J. M. A., & Gray, W. S. (2002). Hamiltonian realizations of nonlinear adjoint operators. *Automatica*, 38(10), 1769-1775. [https://doi.org/10.1016/S0005-1098\(02\)00079-1](https://doi.org/10.1016/S0005-1098(02)00079-1)

Copyright

Other than for strictly personal use, it is not permitted to download or to forward/distribute the text or part of it without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license (like Creative Commons).

The publication may also be distributed here under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license. More information can be found on the University of Groningen website: <https://www.rug.nl/library/open-access/self-archiving-pure/taverne-amendment>.

Take-down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Downloaded from the University of Groningen/UMCG research database (Pure): <http://www.rug.nl/research/portal>. For technical reasons the number of authors shown on this cover page is limited to 10 maximum.

Brief Paper

Hamiltonian realizations of nonlinear adjoint operators[☆]Kenji Fujimoto^a, Jacquélien M.A. Scherpen^{b, *}, W. Steven Gray^c^aDepartment of Systems Science, Graduate School of Informatics, Kyoto University, Uji, Kyoto 611-0011, Japan^bFaculty of Information Technology and Systems, Delft University of Technology, P.O. Box 5031, 2600 GA Delft, Netherlands^cDepartment of Electrical and Computer Engineering, Old Dominion University, Norfolk, VA 23529-0246, USA

Received 29 March 2000; received in revised form 11 December 2001; accepted 25 April 2002

Abstract

This paper addresses the issue of state-space realizations for nonlinear adjoint operators. In particular, the relationships between nonlinear Hilbert adjoint operators, Hamiltonian extensions and port-controlled Hamiltonian systems are established. Then, characterizations of the adjoints of controllability, observability and Hankel operators are derived from this analysis. The state-space realizations of such adjoint operators provide new insights on singular value analysis and duality issues in nonlinear control systems theory. Finally, a duality between the controllability and observability energy functions is proved. © 2002 Elsevier Science Ltd. All rights reserved.

Keywords: Nonlinear systems; State-space realization; Duality; Controllability; Observability

1. Introduction

Adjoint operators play an important role in linear control systems theory. They provide a duality between inputs and outputs that is useful in a variety of problems. For example, properties with respect to the input, e.g. controllability and stabilizability, directly convert to the dual concepts for the output, namely observability and detectability. Furthermore, the connection of adjoint operators with singular values is well known (e.g. Zhou, Doyle, & Glover, 1996) and the concept of singular values has been widely used in the last decades for model reduction purposes. For a linear operator (transfer function) $G(s): E \rightarrow F$ with E and F Hilbert spaces, it is well known that if the operator $G(s)$ has a state-space realization, then its adjoint operator $G^*(s): F \rightarrow E$ can readily be described by the dual state-space realization. The extension of the latter linear adjoint characterization to nonlinear systems is the main topic of this paper. While our main motivation for studying the nonlinear

adjoint concept is to understand the relation between nonlinear singular value functions and the nonlinear Hankel operator, this concept is of importance for many other nonlinear systems concepts which can be considered as extensions of the linear systems theory.

Nonlinear adjoint operators are available in the mathematics literature (see Scherpen & Gray, 2002). The *nonlinear Hilbert adjoint* operator was introduced in Gray and Scherpen (1998), Scherpen and Gray (1999) as a special class of nonlinear adjoint operators and is defined with the help of the Hilbert inner product. Given a mapping $\Sigma: E \rightarrow F$ with Hilbert spaces E and F , a corresponding Hilbert adjoint of Σ is a mapping $\Sigma^*: F \times E \rightarrow E$ such that

$$\langle \Sigma(u), y \rangle_F = \langle u, \Sigma^*(y, u) \rangle_E \quad (1)$$

holds for $\forall u \in E, \forall y \in F$. Conditions for the existence of such operators were given in Scherpen and Gray (2002), but no state-space realization was given. On the other hand, Hamiltonian extensions (Crouch & Van der Schaft, 1987) are commonly used to characterize state-space adjoints of nonlinear control systems. They are based on the variational system realization. Furthermore, in Scherpen and Van der Schaft (1994), Ball and Van der Schaft (1996) and Van der Schaft (2000), Hamiltonian extensions are used extensively as state-space adjoints of nonlinear systems to characterize norm preserving properties. In fact, in the linear case, the Hamiltonian extension of a given operator with a state-space

[☆] This paper has been presented at the IFAC Workshop on Lagrangian and Hamiltonian Methods for Nonlinear Control, March 2000, Princeton, USA. This paper was recommended for publication in revised form by Associate Editor Daizhan Cheng under the direction of Editor Hassan Khalil.

* Corresponding author. Tel.: +31-15-278-6152; fax: +31-15-278-6679.

E-mail address: j.m.a.scherpen@its.tudelft.nl (J.M.A. Scherpen).

realization is the Hilbert adjoint system. However, in the nonlinear setting, this is not such a straightforward issue, and it is shown in this paper that additional dynamics are required for such a relation.

We first develop a relationship between a nonlinear Hilbert adjoint operator and Hamiltonian extensions, where the introduction of additional dynamics is motivated by comparison with the linear case. Then, in order to give a lower dimensional state-space realization of a nonlinear adjoint operator (which requires less restrictive assumptions), system representations falling in the class of port-controlled Hamiltonian systems (Van der Schaft, 2000; Maschke & Van der Schaft, 1992) are used. Such state-space realizations are shown to be particularly convenient for providing realizations of the observability, controllability and Hankel operators. These operators are important in model reduction theory for nonlinear systems in that they supply a set of singular value functions related to input-state and state-output behaviors (Gray & Scherpen, 1998; Scherpen & Gray, 1999; Scherpen & Gray, 2000; Scherpen & Van der Schaft, 1994; Scherpen, 1993). Finally, a certain type of duality (the duality in the sense of Young (Arnold, 1989)) between the observability and controllability energy functions is introduced. This duality relies on the concept of Legendre transformations.

2. State-space realizations of nonlinear adjoint operators

2.1. Adjoint operators and Hamiltonian extensions

In order to relate the nonlinear Hilbert adjoint operators defined in (1) to the existing state-space adjoint notion given by Hamiltonian extensions, consider a possibly time-varying continuous input–output system $\Sigma: L_2^m[t^0, t^1] \rightarrow L_2^r[t^0, t^1]$ defined on a (possibly infinite) time interval $[t^0, t^1] \subset \mathbb{R}$. Its state-space realization is given by

$$u \mapsto y = \Sigma(u): \begin{cases} \dot{x} = f(x, u, t), & x(t^0) = 0, \\ y = h(x, u, t) \end{cases} \quad (2)$$

with $x(t) \in \mathbb{R}^n$, $u(t) \in \mathbb{R}^m$ and $y(t) \in \mathbb{R}^r$. It is assumed that f and h are smooth and that $f(0, 0, t) = 0$ and $h(0, 0, t) = 0$. Throughout the paper we use an abuse of notation by sometimes leaving out the arguments of functions. The Hamiltonian extension of Σ is given by a Hamiltonian control system (Crouch & Van der Schaft, 1987)

$$\begin{aligned} \dot{x} &= \frac{\partial H}{\partial p}^T = f(x, u, t), & x(t^0) &= 0, \\ \dot{p} &= -\frac{\partial H}{\partial x}^T = -\left(\frac{\partial f}{\partial x}^T p + \frac{\partial h}{\partial x}^T u_a\right), & p(t^1) &= 0, \\ y_a &= \frac{\partial H}{\partial u}^T = \frac{\partial f}{\partial u}^T p + \frac{\partial h}{\partial u}^T u_a \\ y &= \frac{\partial H}{\partial u_a}^T = h(x, u, t) \end{aligned} \quad (3)$$

with the Hamiltonian

$$H(x, p, u, u_a, t) := p^T f(x, u, t) + u_a^T h(x, u, t). \quad (4)$$

We now prove some properties of this system which are related to the nonlinear Hilbert adjoint operator.

Proposition 1. Consider the Hamiltonian extension (3) of Σ . Suppose f and h are time-invariant, i.e. $f = f(x, u)$ and $h = h(x, u)$. Define scalar-valued functions H_1 , H_2 and H_3 as

$$H_1 = H - \frac{\partial H}{\partial u_a} u_a, \quad H_2 = H - \frac{\partial H}{\partial u} u,$$

$$H_3 = H - \frac{\partial H}{\partial u} u - \frac{\partial H}{\partial u_a} u_a.$$

Then the following relations hold:

$$\begin{aligned} \frac{dH}{dt} &= y_a^T \dot{u} + y^T \dot{u}_a, & \frac{dH_1}{dt} &= y_a^T \dot{u} - \dot{y}^T u_a \\ \frac{dH_2}{dt} &= -\dot{y}_a^T u + y^T \dot{u}_a, & \frac{dH_3}{dt} &= -\dot{y}_a^T u - \dot{y}^T u_a. \end{aligned} \quad (5)$$

Proof. The first equation in (5) follows from

$$\begin{aligned} \frac{dH}{dt} &= \frac{\partial H}{\partial x} \dot{x} + \frac{\partial H}{\partial p} \dot{p} + \frac{\partial H}{\partial u} \dot{u} + \frac{\partial H}{\partial u_a} \dot{u}_a \\ &= \frac{\partial H}{\partial x} \frac{\partial H}{\partial p}^T - \frac{\partial H}{\partial p} \frac{\partial H}{\partial x}^T + y_a^T \dot{u} + y^T \dot{u}_a = y_a^T \dot{u} + y^T \dot{u}_a. \end{aligned}$$

Then the time derivative of the other functions are obtained straightforwardly. $\square$

This proposition shows that the Hamiltonian extension has a close relationship to nonlinear Hilbert adjoint operators. For example, the property for H_1 in (5) implies the mapping $u_a \mapsto y_a$ is the nonlinear Hilbert adjoint of the variational mapping $\dot{u} \mapsto \dot{y}$, while the property for H_2 shows that the original mapping $u \mapsto y$ coincides with the adjoint of the variational map $\dot{u}_a \mapsto \dot{y}_a$. This relation can be utilized to derive a state-space realization of a nonlinear Hilbert adjoint operator of an input-affine nonlinear system under some additional assumptions. The property for H_3 in (5) is similar to a basic property of *physical* Hamiltonian control systems, namely the so-called *energy balancing* (Crouch & Van der Schaft, 1987). By studying those properties, it becomes clear that the Hamiltonian extension of Σ is not a state-space realization of the nonlinear Hilbert adjoint of Σ . However, the above proposition does provide a tool to obtain such state-space realization via the Hamiltonian extensions of Σ as can be seen in the next corollary.

Corollary 2. Consider the input–output system Σ with state-space realization (2) defined for $t \in [t^0, t^1] \subset \mathbb{R}$. Suppose f and h are time-invariant and input-affine, i.e. $f \equiv g_0(x) + g(x)u$ and $h \equiv k_0(x) + k(x)u$ for some smooth

functions g_0 , g , k_0 and k . Suppose moreover that

$$u \in L_2^m[t^0, t^1], \quad u_b \in L_2^r[t^0, t^1]$$

$$\Rightarrow \|x(t^1)\| < \infty, \quad \|p_1(t^0)\| < \infty, \quad \|p_2(t^0)\| < \infty \quad (6)$$

holds for the state-space system $(u_b, u) \mapsto y_b = \Sigma^*(u_b, u)$:

$$\begin{cases} \dot{x} = g_0(x) + g(x)u, & x(t^0) = 0, \\ \dot{p}_1 = -\frac{\partial g_0}{\partial x}^T p_1 - \frac{\partial k_0}{\partial x}^T p_2, & p_1(t^1) = 0, \\ \dot{p}_2 = u_b, & p_2(t^1) = 0, \\ y_b = \left(\frac{\partial(g^T p_1)}{\partial x} + \frac{\partial(k^T p_2)}{\partial x} \right) g_0(x) \\ \quad - g^T(x) \left(\frac{\partial g_0}{\partial x}^T p_1 + \frac{\partial k_0}{\partial x}^T p_2 \right) + k^T(x)u_b. \end{cases} \quad (7)$$

Then a state-space realization of the nonlinear Hilbert adjoint $\Sigma^*: L_2^m[t^0, t^1] \times L_2^r[t^0, t^1] \rightarrow L_2^m[t^0, t^1]$ is given by (7).

Proof. System (7) is derived by defining $u_b := \dot{u}_a$, $y_b := \dot{y}_a$ and $p_2 := u_a$ within the Hamiltonian extension (3). Note that from the input-affine form of f and h , we have

$$H_2(x, p_1, p_2) = p_1^T g_0(x) + p_2^T k_0(x).$$

The initial condition of (7) and $g_0(0) = 0$ and $k_0(0) = 0$ imply that

$$H_2(x(t^0), p_1(t^0), p_2(t^0)) = H_2(x(t^1), p_1(t^1), p_2(t^1)) = 0.$$

Then it follows from (5) in Proposition 1 that

$$\begin{aligned} 0 &= [H_2]_{t=t^0}^{t=t^1} = \int_{t^0}^{t^1} \frac{dH_2}{dt} dt = \langle y, \dot{u}_a \rangle_{L_2^r[t^0, t^1]} - \langle u, \dot{y}_a \rangle_{L_2^m[t^0, t^1]} \\ &= \langle y, u_b \rangle_{L_2^r[t^0, t^1]} - \langle u, y_b \rangle_{L_2^m[t^0, t^1]}. \end{aligned}$$

Substituting $y = \Sigma(u)$ and $y_b = \Sigma^*(u_b, u)$ yields the defining equation of a nonlinear Hilbert adjoint operator

$$\langle \Sigma(u), u_b \rangle_{L_2^r[t^0, t^1]} = \langle u, \Sigma^*(u_b, u) \rangle_{L_2^m[t^0, t^1]}$$

and this completes the proof. $\square$

Observe that state-space realization (7) has $(2n + r)$ states, and corresponds in the linear case to $(s\Sigma(s)(1/s))^* = s\Sigma^*(s)(1/s)$. Intuitively this follows from the original definition of the Hamiltonian extension as the adjoint of the variational system. Of course this input–output mapping coincides with $\Sigma^*(s)$ for a linear system, but not generally for nonlinear systems. Furthermore, observe that this realization requires the restrictive assumption (6) because otherwise $t \in (-\infty, \infty)$ in (6), i.e. $t^0 \rightarrow -\infty$ and $t^1 \rightarrow \infty$, implies the anti-stability of a non-minimum phase operator $\Sigma^*(s)(1/s)$. Hence, in general, assumption (6) holds only for a finite time interval $t \in [t^0, t^1]$.

2.2. Adjoint operators and port-controlled Hamiltonian systems

The state-space realizations of a nonlinear Hilbert adjoint operator based on Hamiltonian extensions given in Corollary 2 are somewhat limited because of the need for restrictive assumptions, i.e., they are available only for input-affine nonlinear systems, they are $(2n + r)$ -dimensional, and they require a restrictive anti-stability assumption (6). We now produce a more general state-space formulation that is based on the concept of port-controlled Hamiltonian systems (e.g., Van der Schaft, 2000; Maschke & Van der Schaft, 1992).

Consider the input–output system Σ in (2). This system can be regarded as an operator $\hat{\Sigma}: \mathbb{R}^n \times L_2^m[t^0, t^1] \rightarrow \mathbb{R}^n \times L_2^r[t^0, t^1]$ with a state-space realization

$$(x^0, u) \mapsto (x^1, y) = \hat{\Sigma}(x^0, u): \begin{cases} \dot{x} = f(x, u, t), & x(t^0) = x^0, \\ y = h(x, u, t), \\ x^1 = x(t^1). \end{cases} \quad (8)$$

By a specialized version of the Fundamental Theorem of Integral Calculus (e.g. Milnor, 1963), it is well known that f and h can be factorized. These factorizations can be used in combination with the concept of a port-controlled Hamiltonian system to obtain a $2n$ -dimensional state-space realization of a nonlinear Hilbert adjoint operator of $\hat{\Sigma}$, as is done in the following proposition.

Proposition 3. Consider the operator $\hat{\Sigma}: \mathbb{R}^n \times L_2^m[t^0, t^1] \rightarrow \mathbb{R}^n \times L_2^r[t^0, t^1]$ with a state-space realization as defined in (8) and with $t \in [t^0, t^1] \subset \mathbb{R}$. Furthermore, consider the corresponding port-controlled Hamiltonian system $H_{\hat{\Sigma}}: \mathbb{R}^{2n} \times L_2^{m+r}[t^0, t^1] \rightarrow \mathbb{R}^{2n} \times L_2^{m+r}[t^0, t^1]$ given by

$$(x^0, p^1, \hat{u}) \mapsto (x^1, p^0, \hat{y}) = H_{\hat{\Sigma}}(x^0, p^1, \hat{u}): \begin{cases} \dot{\hat{x}} = \hat{J}(\hat{x}, \hat{u}, t) \frac{\partial \hat{H}}{\partial \hat{x}}^T + \hat{g}(\hat{x}, \hat{u}, t) \hat{u}, \\ \hat{y} = \hat{g}^T(\hat{x}, \hat{u}, t) \frac{\partial \hat{H}}{\partial \hat{x}}^T + \hat{D}(\hat{x}, \hat{u}, t) \hat{u}, \\ \hat{x}(t^0) = (x^0, p^0), \\ \hat{x}(t^1) = (x^1, p^1) \end{cases} \quad (9)$$

with $\hat{x}(t) := (x(t), p(t)) \in \mathbb{R}^n \times \mathbb{R}^n$, $\hat{u}(t) := (u(t), u_a(t)) \in \mathbb{R}^m \times \mathbb{R}^r$, $\hat{y}(t) := (y_a(t), -y(t)) \in \mathbb{R}^m \times \mathbb{R}^r$ and

$$\begin{aligned} \hat{H} &:= p^T x, \quad \hat{J} := \begin{pmatrix} 0 & A \\ -A^T & 0 \end{pmatrix}, \\ \hat{g} &:= \begin{pmatrix} B & 0 \\ 0 & -C^T \end{pmatrix}, \quad \hat{D} := \begin{pmatrix} 0 & D^T \\ -D & 0 \end{pmatrix}. \end{aligned} \quad (10)$$

Here $A(x, u, t) \in \mathbb{R}^{n \times n}$, $B(x, u, t) \in \mathbb{R}^{n \times m}$, $C(x, u, t) \in \mathbb{R}^{r \times n}$ and $D(x, u, t) \in \mathbb{R}^{r \times m}$ are appropriate matrices such that

$$f(x, u, t) = A(x, u, t)x + B(x, u, t)u, \quad (11)$$

$$h(x, u, t) = C(x, u, t)x + D(x, u, t)u \quad (12)$$

hold. Suppose that

$$\begin{aligned} \|x^0\| < \infty, \quad \|p^1\| < \infty, \quad u \in L_2^m[t^0, t^1], \quad u_a \in L_2^r[t^0, t^1] \\ \Rightarrow \|x^1\| < \infty, \quad \|p^0\| < \infty. \end{aligned} \quad (13)$$

Then the mapping $(x^0, p^1, u, u_a) \mapsto (p^0, y_a)$ corresponding to the state-space realization (9) is a state-space realization of a nonlinear Hilbert adjoint operator $\hat{\Sigma}^* : \mathbb{R}^{2n} \times L_2^m[t^0, t^1] \times L_2^r[t^0, t^1] \rightarrow \mathbb{R}^n \times L_2^r[t^0, t^1]$ of $\hat{\Sigma}$.

Proof. Since (9) is a time-varying port-controlled Hamiltonian system (see e.g., Fujimoto & Sugie, 1998; Fujimoto, 2000), we have that

$$\begin{aligned} \frac{d\hat{H}}{dt} &= \frac{\partial \hat{H}}{\partial \hat{x}} \left(\hat{J} \frac{\partial \hat{H}}{\partial \hat{x}} + \hat{g}\hat{u} \right) \\ &= \frac{\partial \hat{H}}{\partial \hat{x}} \hat{g}\hat{u} = \left(\frac{\partial \hat{H}}{\partial \hat{x}} \hat{g} + \hat{u}^T \hat{D}^T \right) \hat{u} \\ &= \hat{y}^T \hat{u} = y_a^T u - y^T u_a. \end{aligned}$$

Integrating this equation with $\hat{H} = p^T x$ yields

$$\begin{aligned} \langle (x^1, y), (p^1, u_a) \rangle_{\mathbb{R}^n \times L_2^r[t^0, t^1]} \\ = \langle (x^0, u), (p^0, y_a) \rangle_{\mathbb{R}^n \times L_2^r[t^0, t^1]}. \end{aligned} \quad (14)$$

Substituting $(p^0, y_a) = \hat{\Sigma}^*((p^1, u_a), (x^0, u))$ and $(x^1, y) = \hat{\Sigma}(x^0, u)$ yields

$$\begin{aligned} \langle \hat{\Sigma}(x^0, u), (p^1, u_a) \rangle_{\mathbb{R}^n \times L_2^r} \\ = \langle (x^0, u), \hat{\Sigma}^*((p^1, u_a), (x^0, u)) \rangle_{\mathbb{R}^n \times L_2^m}. \end{aligned}$$

This proves the proposition. $\square$

It should be noted that the characterization given in the above proposition yields a coordinate dependent state-space characterization of a nonlinear Hilbert adjoint in the sense that if we apply a coordinate transformation, the port-controlled Hamiltonian structure is lost. This is due to the fact that the Hamiltonian given in (10) is intrinsically coordinate dependent. On the other hand, it provides very natural state-space realizations of adjoint operators because it requires rather mild assumptions. The Hamiltonian extension given in the previous subsection is coordinate free, i.e., the Hamiltonian structure is maintained due to the fact that a coordinate transformation is canonical in this case. Of course both the port-controlled Hamiltonian adjoint characterization and the Hamiltonian extension coincide with each other in the linear case. Further, as in Corollary 2,

the following corollary yields a state-space realization for the nonlinear Hilbert adjoint of Σ in (2) when the initial conditions are set to zero.

Corollary 4. Consider the system Σ in (2) with the initial condition $x^0=0$ and let $\Sigma : L_2^m[t^0, t^1] \rightarrow L_2^r[t^0, t^1]$ denote the mapping $u \mapsto y$. Suppose the assumption (13) holds. Then a state-space realization of the nonlinear Hilbert adjoint $\Sigma^* : L_2^m[t^0, t^1] \times L_2^r[t^0, t^1] \rightarrow L_2^m[t^0, t^1]$ of Σ is given by

$$\begin{aligned} (u_a, u) \mapsto y_a = \Sigma^*(u_a, u): \\ \begin{cases} \dot{x} = f(x, u, t), & x(t^0) = 0, \\ \dot{p} = -A^T(x, u, t)p - C^T(x, u, t)u_a, & p(t^1) = 0, \\ y_a = B^T(x, u, t)p + D^T(x, u, t)u_a. \end{cases} \end{aligned} \quad (15)$$

3. Energy functions and operators

3.1. Observability, controllability and Hankel operators

In this section, the results of Section 2 are applied to obtain state-space realizations for nonlinear Hilbert adjoints of some useful operators in nonlinear control theory, i.e., the Hankel, observability and controllability operators. These operators were first introduced in Gray and Scherpen (1998) and Scherpen and Gray (1999), and can be seen as natural extensions from the linear theory (Zhou et al., 1996). Only time-invariant, input-affine systems are considered without direct feedthrough, that is

$$\Sigma: \begin{cases} \dot{x} = f(x) + g(x)u, \\ y = h(x) \end{cases} \quad (16)$$

defined for $t \in (-\infty, \infty)$. Assume for the remainder of the paper that $f(x)$ is asymptotically stable. State-space realizations which describe the observability and controllability operators are given by

$$x^0 \mapsto y = \mathcal{O}(x^0): \begin{cases} \dot{x} = f(x), & x(0) = x^0, \\ y = h(x), \end{cases} \quad (17)$$

$$u \mapsto x^1 = \mathcal{C}(u):$$

$$\begin{cases} \dot{x} = f(x) + g(x)\mathcal{F}_-(u), & x(-\infty) = 0, \\ x^1 = x(0). \end{cases} \quad (18)$$

Here $\mathcal{F}_- : L_2^m[0, \infty) \rightarrow L_2^m(-\infty, 0]$ denotes the so-called *time flipping operator* defined for $t \leq 0$ by $\mathcal{F}_-(u)(t) = u(-t)$ and zero otherwise. Furthermore, the Hankel operator $\mathcal{H} : L_2^m[0, \infty) \rightarrow L_2^r[0, \infty)$ of Σ is given by

$$\mathcal{H} = \mathcal{O} \circ \mathcal{C} = \Sigma \circ \mathcal{F}_- \quad (19)$$

mapping past inputs to future outputs. The original definitions of these operators via Chen–Fliess functional expansions along with more detailed discussions can be found in Gray and Scherpen (1998), Scherpen and Gray (1999) and Gray and Scherpen (2002). State-space realizations for

nonlinear Hilbert adjoint operators of $\mathcal{O}$, $\mathcal{C}$ and $\mathcal{H}$ are given as follows.

Proposition 5. Consider the operator Σ with state-space realization (16). Suppose that assumption (13) in Proposition 3 holds for the relevant port-controlled Hamiltonian system (9). Then state-space realizations of $\mathcal{O}^*: L_2^r[0, \infty) \times \mathbb{R}^n \rightarrow \mathbb{R}^n$, $\mathcal{C}^*: \mathbb{R}^n \times L_2^m[0, \infty) \rightarrow L_2^m[0, \infty)$ and $\mathcal{H}^*: L_2^r[0, \infty) \times L_2^m[0, \infty) \rightarrow L_2^m[0, \infty)$ are given by

$$p^0 = \mathcal{O}^*(x^0, u_a): \begin{cases} \dot{x} = f(x), & x(0) = x^0, \\ \dot{p} = -A^T(x)p \\ \quad - C^T(x)u_a, & p(\infty) = 0, \\ p^0 = p(0), \end{cases} \quad (20)$$

$$y_a = \mathcal{C}^*(p^1, u): \begin{cases} \dot{x} = f(x) + g(x)\mathcal{F}_-(u), & x(-\infty) = 0, \\ \dot{p} = -A^T(x)p, & p(0) = p^1, \\ y_a = \mathcal{F}_+(g^T(x)p), \end{cases} \quad (21)$$

$$y_a = \mathcal{H}^*(u_a, u): \begin{cases} \dot{x} = f(x) + g(x)\mathcal{F}_-(u), & x(-\infty) = 0, \\ \dot{p} = -A^T(x)p \\ \quad - C^T(x)u_a, & p(\infty) = 0, \\ y_a = \mathcal{F}_+(g^T(x)p) \end{cases} \quad (22)$$

with matrices $A(x) \in \mathbb{R}^{n \times n}$ and $C(x) \in \mathbb{R}^{r \times n}$ such that $f(x) \equiv A(x)x$ and $h(x) \equiv C(x)x$ hold. Here $\mathcal{F}_+: L_2^m(-\infty, 0] \rightarrow L_2^m[0, \infty)$ denotes yet another time flipping operator defined for $t \geq 0$ by $\mathcal{F}_+(u)(t) = u(-t)$ and zero otherwise.

Proof. Substitute $t^0 = 0$, $t^1 = \infty$, $p^1 = p(\infty) = 0$ and $u = 0$ into Eq. (14) to obtain

$$\begin{aligned} \langle y, u_a \rangle_{L_2^r[0, \infty)} &= \langle (x^1, y), (0, u_a) \rangle_{\mathbb{R}^n \times L_2^r[0, \infty)} \\ &= \langle (x^0, 0), (p^0, y_a) \rangle_{\mathbb{R}^n \times L_2^m[0, \infty)} = \langle x^0, p^0 \rangle_{\mathbb{R}^n}. \end{aligned}$$

Substituting, moreover, $y = \mathcal{O}(x^0)$ and $p^0 = \mathcal{O}^*(x^0, u_a)$ as in (20) yields

$$\langle \mathcal{O}(x^0), u_a \rangle_{L_2^r[0, \infty)} = \langle x^0, \mathcal{O}^*(u_a, x^0) \rangle_{\mathbb{R}^n}.$$

This proves the first part. The second part can be proven in a similar way. Substituting $t^0 = -\infty$, $t^1 = 0$, $x^0 = x(-\infty) = 0$ and $u_a = 0$ into Eq. (14) yields

$$\begin{aligned} \langle x^1, p^1 \rangle_{\mathbb{R}^n} &= \langle (x^1, y), (p^1, 0) \rangle_{\mathbb{R}^n \times L_2^r(-\infty, 0]} \\ &= \langle (0, \mathcal{F}_-(u)), (p^0, y_a) \rangle_{\mathbb{R}^n \times L_2^m(-\infty, 0]} \\ &= \langle \mathcal{F}_-(u), y_a \rangle_{L_2^r(-\infty, 0]} = \langle u, \mathcal{F}_+(y_a) \rangle_{L_2^m[0, \infty)}. \end{aligned} \quad (23)$$

Then letting $x^1 = \mathcal{C}(u)$ and $y_a = \mathcal{C}^*(p^1, u)$ in (21) yields

$$\langle \mathcal{C}(u), p^1 \rangle_{\mathbb{R}^n} = \langle u, \mathcal{C}^*(p^1, u) \rangle_{L_2^m(-\infty, 0]}.$$

This proves the second part. The last part is proven by noting that Eq. (23) implies that $\mathcal{F}_-^* = \mathcal{F}_+$ and $\mathcal{F}_+^* = \mathcal{F}_-$. Combining this with the linear adjoint property of the time flipping operators, the results of Scherpen and Gray, 2002, and the definition of the Hankel operator given by (19) gives

$$\begin{aligned} \mathcal{H}^*(u_a, u) &= (\Sigma \circ \mathcal{F}_-)^*(u_a, u) = \mathcal{F}_-^* \circ \Sigma^*(u_a, \mathcal{F}_-(u)) \\ &= \mathcal{F}_+ \circ \Sigma^*(u_a, \mathcal{F}_-(u)). \end{aligned}$$

This completes the proof. $\square$

3.2. Observability and controllability functions

In this subsection, duality relationships among the observability and controllability functions, operators and nonlinear Gramian extensions are discussed. We begin with the definition of the energy functions, also referred to as the observability and controllability functions.

Definition 6 (Scherpen, 1993). The observability function, $L_o(x)$, and the controllability function, $L_c(x)$, of Σ as in (16) are defined by

$$L_o(x^0) := \frac{1}{2} \int_0^\infty \|y(t)\|^2 dt, \quad x(0) = x^0, \quad u(t) \equiv 0, \quad (24)$$

$$L_c(x^1) := \min_{\substack{u \in L_2^m(-\infty, 0] \\ x(-\infty)=0, x(0)=x^1}} \frac{1}{2} \int_{-\infty}^0 \|u(t)\|^2 dt. \quad (25)$$

It is assumed throughout that L_o and L_c exist and are smooth. These functions are closely related to observability and controllability operators and Gramians (Gray & Scherpen, 1998; Scherpen & Gray, 1999; Gray & Scherpen, 2002). Specifically, the relations between the observability function, operator and “Gramian” are given by

$$\begin{aligned} L_o(x^0) &= \frac{1}{2} \|\mathcal{O}(x^0)\|_{L_2^r}^2 = \frac{1}{2} \langle x^0, \mathcal{O}^*(\mathcal{O}(x^0), x^0) \rangle_{\mathbb{R}^n} \\ &= \frac{1}{2} \langle x^0, p^0 \rangle_{\mathbb{R}^n} =: \frac{1}{2} \langle x^0, \phi(x^0) \rangle_{\mathbb{R}^n}. \end{aligned} \quad (26)$$

Here, $p^0 = p(0)$ is the initial state of the state-space realization of $\mathcal{O}^*$ in (20) with input $(x^0, u_a) = (x^0, \mathcal{O}(x^0))$. The function $\phi(x^0)$ can always be expressed as $\phi(x^0) = Q(x^0)x^0$ using a square symmetric matrix $Q(x^0)$. In the linear case this matrix equals the observability Gramian. Furthermore, note that the relation

$$L_o(x(t)) = \frac{1}{2} \langle x(t), p(t) \rangle_{\mathbb{R}^n} \quad (27)$$

holds along the trajectory of the state-space realization (20) of $\mathcal{O}^*(x^0, \mathcal{O}(x^0))$. Particularly, in the case where $x(t) \in \mathbb{R}$, the function ϕ in Eq. (26) is readily computed as follows.

Example 7. Consider the system (16) with $n = m = r = 1$, i.e., $x(t), u(t), y(t) \in \mathbb{R}$. The observability operator and its Hilbert adjoint are given by (17) and (20), respectively, with the unique decomposition $A(x) = f(x)/x$ and $C(x) = h(x)/x$. Since ϕ is unique in the case $n = 1$, it follows from (26) and (27) that the states of $\mathcal{O}^*(x^0, \mathcal{O}(x^0))$ satisfy $(x(t), p(t)) = (x(t), \phi(x(t)))$ for $\forall t \in [0, \infty)$ with a scalar-valued function $\phi: \mathbb{R} \rightarrow \mathbb{R}$ satisfying $\phi(0) = 0$. Therefore

$$\dot{p} = -\frac{f(x)}{x} \phi(x) - \frac{h(x)}{x} h(x) \equiv \frac{d\phi(x)}{dx} \dot{x} = \frac{d\phi(x)}{dx} f(x).$$

The solution of this equation is given by

$$\phi(x) = -\frac{1}{x} \int_0^x \frac{h(\xi)^2}{f(\xi)} d\xi.$$

As explained above, the function $(\phi(x)/x)$ is the nonlinear extension of the observability Gramian. Furthermore, the function ϕ can be used to calculate L_o via (26). For example, take $f(x) = -x$ and $h(x) = x^2$, then it is straightforwardly computed that $\phi(x) = (1/4)x^3$, and $L_o(x) = (1/8)x^4$.

In the controllability case, there does not exist as nice a relation for $\mathcal{C}^*$. Nevertheless, we are able to obtain a duality result along the linear lines of thinking in the following proposition. It concerns a duality between the observability and controllability functions.

Proposition 8. Consider the system Σ with the state-space realization (16). It is assumed that $f(x)$ is asymptotically stable and that $L_o(x)$ and $L_c(x)$ exist and are smooth. Consider the system

$$\begin{aligned} \dot{p} &= A^T(\phi_i(p))p + C^T(\phi_i(p))u_a, \\ y_a &= g^T(\phi_i(p))p \end{aligned} \quad (28)$$

with the subscript $i \in \{c, o\}$. Let $x = \phi_c(p)$ denote the inverse mapping of $p = (\partial L_c(x)/\partial x)^T$. Suppose that (28) has observability function $\tilde{L}_o(p)$ and that $i = c$. Then $\tilde{L}_o(p)$ is given by the Legendre transformation

$$\tilde{L}_o(p) = -L_c(x) + p^T x. \quad (29)$$

Let $x = \phi_o(p)$ denote the inverse mapping of $p = (\partial L_o(x)/\partial x)^T$. Suppose that (28) has controllability function $\tilde{L}_c(p)$ and that $i = o$. Then $\tilde{L}_c(p)$ is given by the Legendre transformation

$$\tilde{L}_c(p) = -L_o(x) + p^T x. \quad (30)$$

Proof. It follows from Scherpen (1993) that the controllability function $L_o(x)$ of the system Σ is the unique anti-stabilizing solution of the Hamilton–Jacobi equation

$$\frac{\partial L_c}{\partial x}(x)f(x) + \frac{1}{2} \frac{\partial L_c}{\partial x}(x)g(x)g^T(x) \frac{\partial L_c}{\partial x}(x) = 0, \quad (31)$$

and the observability function $\tilde{L}_o(p)$ of (28) for $i = c$ is the unique solution of the Lyapunov equation

$$\begin{aligned} \frac{\partial \tilde{L}_o}{\partial p}(p)A(\phi_c(p))^T p \\ + \frac{1}{2} p^T g(\phi_c(p))g^T(\phi_c(p))p = 0. \end{aligned} \quad (32)$$

Here $x = \phi_c(p)$ is the inverse mapping of $p = (\partial L_c(x)/\partial x)^T$. By applying this transformation it follows that (31) and (32) are the same. And thus, a solution for (32) is given by the Legendre transformation (29) which has the property that $(\partial \tilde{L}_o(p)/\partial p) = \phi_c^T(p)$ holds. Furthermore, this is the observability function of the p -subsystem because the Lyapunov equation has a unique solution. This proves the first part. The second part can be proven in a similar way. $\square$

Thus, we can prove a certain type of duality between input and output. This is similar to the linear case. Legendre transformations define for physical Hamiltonian systems the physical dual coordinates. However, due to the difference between the adjoint notion and the duality result above, it follows that duality does not hold in the exact same way for the general case, although some similarity with physical systems is retained. Legendre transformations transform a convex function into another convex function, which is necessary for relating the controllability and observability of “dual” dynamics with the original dynamics. The type of duality of Proposition 8 is the so-called *duality in the sense of Young* (Arnold, 1989), which often appears in the literature of both optimal control (Young, 1969) and optimization theory (Walsh, 1975).

4. Conclusion

This paper presented state-space realizations for nonlinear adjoint operators. In particular, the relationships between nonlinear Hilbert adjoint operators, Hamiltonian extensions and port-controlled Hamiltonian systems were established. A characterization of the controllability, observability, and Hankel adjoint operators and functions was then derived using these results. Finally, the duality in the sense of Young was shown to apply to controllability and observability functions in the nonlinear setting.

Acknowledgements

The authors would like to thank Professor Arjan van der Schaft of the University of Twente for his insightful suggestions.

References

- Arnold, V. I. (1989). *Mathematical methods of classical mechanics* (2nd ed.). New York: Springer.

- Ball, J. A., & Van der Schaft, A. J. (1996). J -inner-outer factorization, J -spectral factorization, and robust control for nonlinear systems. *IEEE Transaction on Automatic Control*, AC-41(3), 379–392.
- Crouch, P. E., & Van der Schaft, A. J. (1987). Variational and Hamiltonian control systems. In *Lecture notes on control and information science*, Vol. 101. Berlin: Springer.
- Fujimoto, K. (2000). *Synthesis and analysis of nonlinear control systems based on transformations and factorizations*. Ph. D. thesis, Kyoto University, Kyoto, Japan.
- Fujimoto, K., & Sugie, T. (1998). Canonical transformation and stabilization of generalized Hamiltonian systems. In *Proceedings of the fourth IFAC symposium on Nonlinear Control Systems* (pp. 544–549).
- Gray, W. S., & Scherpen, J. M. A. (1998). Hankel operators and Gramians for nonlinear systems. In *Proceedings of the 37th IEEE Conference on Decision and Control* (pp. 3349–3353).
- Gray, W. S., & Scherpen, J. M. A. (2002). Hankel singular value functions from Schmidt pairs for nonlinear input–output systems. In *Proceedings of the American Control Conference* (pp. 3540–3545).
- Maschke, B. M. J., & Van der Schaft, A. J. (1992). Port-controlled Hamiltonian systems: Modeling origins and system-theoretic properties. In *Proceedings of the IFAC symposium on nonlinear control systems* (pp. 282–288).
- Milnor, J. W. (1963). Morse theory. In *Annals of mathematical studies*, Vol. 51. Princeton, NJ: Princeton University Press.
- Scherpen, J. M. A. (1993). Balancing for nonlinear systems. *Systems & Control Letters*, 21, 143–153.
- Scherpen, J. M. A., & Gray, W. S. (1999). On singular value functions and Hankel operators for nonlinear systems. In *Proceedings of the American Control Conference* (pp. 2360–2364).
- Scherpen, J. M. A., & Gray, W. S. (2000). Minimality and local state decompositions of a nonlinear state-space realization using energy functions. *IEEE Transactions on Automatic Control*, AC-45(11), 2079–2086.
- Scherpen, J. M. A., & Gray, W. S. (2002). Nonlinear Hilbert adjoints: Properties and applications to Hankel singular value analysis. *Nonlinear analysis: theory, methods and applications*, to appear.
- Scherpen, J. M. A., & Van der Schaft, A. J. (1994). Normalized coprime factorization and balancing for unstable nonlinear systems. *International Journal of Control*, 60(6), 1193–1222.
- Van der Schaft, A. J. (2000). *L_2 -gain and passivity techniques in nonlinear control*. London, Berlin: Springer.
- Walsh, G. R. (1975). *Methods of optimization*. London: Wiley.
- Young, L. C. (1969). *Lectures on the calculus of variations and optimal control theory*. Philadelphia: W. B. Saunders Company.
- Zhou, K., Doyle, J. C., & Glover, K. (1996). *Robust and optimal control*. Upper Saddle River, NJ: Prentice-Hall.

is a Research Associate at the Graduate School of Informatics at Kyoto University, Japan. His research interests include nonlinear systems theory and control.

Tokyo, Japan and the Old Dominion University, VA, USA. Her research interests include nonlinear model reduction methods, realization theory, nonlinear control methods, with in particular modeling and control of physical systems with applications to electrical circuits. She is an Associate Editor of the IEEE Transactions on Automatic Control.

W. Steven Gray received the B.S. degree in electrical engineering from Purdue University in 1983. He then received the M.S. degree in electrical engineering in 1985, the M.S. degree in applied mathematics in 1988, and the Ph.D. in electrical engineering in 1989, all from the Georgia Institute of Technology. Currently, he is on the Electrical and Computer Engineering Faculty of Old Dominion University in Norfolk, VA. His research interests are in modeling and control theory for nonlinear systems. Dr. Gray is a member of the Institute of Electrical and Electronics Engineers, The American Mathematical Society, The Society of Industrial and Applied Mathematics, and The Mathematical Association of America.

Kenji Fujimoto was born in Osaka, Japan in 1971. He received his B.Sc. and M.Sc. degrees in engineering and his Ph.D. degree in informatics from Kyoto University, Japan, in 1994, 1996 and 2001, respectively. From 1997 to 1998 he was a Research Associate at the Graduate School of Engineering at Kyoto University, Japan. From 1999 to 2000 he was a Research Fellow at the Department of Electrical Engineering at Delft University of Technology, The Netherlands. His current position

Jacqueliën M.A. Scherpen received her M.Sc. and Ph.D. degree in Applied Mathematics from the University of Twente, The Netherlands, in 1990 and 1994, respectively. Currently, she is an associate professor in the Control Systems Engineering group of the faculty of Information Technology and Systems of Delft University of Technology, The Netherlands. She has held visiting research positions at the Université de Compiègne, France, SUPELEC, Gif-sur-Yvette, France, the University of