University of Groningen

Nonlinear Disturbance Attenuation Controller for Turbo-Generators in Power Systems via Recursive Design

Cao, M.; Shen, T.L.; Song, Y.H.; Mei, S.W.

Published in:

Proceedings of the 2002 International Conference on Control Applications Control Applications

IMPORTANT NOTE: You are advised to consult the publisher's version (publisher's PDF) if you wish to cite from it. Please check the document version below.

Document Version

Publisher's PDF, also known as Version of record

Publication date:

2002

[Link to publication in University of Groningen/UMCG research database](#)

Citation for published version (APA):

Cao, M., Shen, T. L., Song, Y. H., & Mei, S. W. (2002). Nonlinear Disturbance Attenuation Controller for Turbo-Generators in Power Systems via Recursive Design. In *Proceedings of the 2002 International Conference on Control Applications Control Applications* (Vol. 2, pp. 938-943). University of Groningen, Research Institute of Technology and Management.

Copyright

Other than for strictly personal use, it is not permitted to download or to forward/distribute the text or part of it without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license (like Creative Commons).

The publication may also be distributed here under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license. More information can be found on the University of Groningen website: <https://www.rug.nl/library/open-access/self-archiving-pure/taverne-amendment>.

Take-down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Downloaded from the University of Groningen/UMCG research database (Pure): <http://www.rug.nl/research/portal>. For technical reasons the number of authors shown on this cover page is limited to 10 maximum.

NONLINEAR DISTURBANCE ATTENUATION CONTROLLER FOR TURBO- GENERATORS IN POWER SYSTEMS VIA RECURSIVE DESIGN

Y.Z. SUN¹, M. CAO¹, S.W. MEI¹, T.L. SHEN², Y.H. SONG³

1. Tsinghua University, China; 2. Sophia University, Japan; 3. Brunel University, UK

Abstract: The paper proposes a nonlinear robust controller for steam governor control in power systems. Based on dissipation theory, an innovative recursive design method is presented to construct the storage function of single machine infinite bus (SMIB) and multi-machine power systems. Furthermore, the nonlinear L_2 -gain disturbance attenuation control strategy is achieved for speed governor control of turbo-generators without requiring the solution of HJI inequality. With multi-machine power system control, all the variables in the control law are only relevant to the state variables of the local generator, thus a decentralized control strategy is achieved. Simulation results of a 4-machine system show that the controller can enhance power transient stability and dynamic performances.

Keywords: Recursive design; Nonlinear disturbance attenuation control; Decentralized control; Multi-machine power system

1. Introduction

Modern power systems have developed into large, distributed and highly nonlinear systems with complicated and random disturbances. To design robust nonlinear decentralized controller is under heavy investigation for improving power system transient stability and dynamic performances. Speed governor control for large-scale turbo-generators is one of the most efficient and effective methods to enhance system stability when large disturbances occur. With the development of modern control theory in the recent 20 years, various control strategies are applied to the speed

governor control systems, including linear optimal control, robust control and nonlinear control. With the application of differential geometric approach [1], decentralized stabilization problem for multi-machine power systems is successfully resolved by exact feedback linearization. However, its requirement for a precise mathematical model limits its application into practical electric engineering, in which various uncertainties exist, such as internal and exogenous disturbances and measurement errors. Ref [2] introduces nonlinear robust control method into speed governor controller design. However the H_∞ control law is achieved from the system after feedback linearization, so it loses the strict robustness for the original nonlinear system.

This paper adopts the recursive design technique [3][4] to design nonlinear disturbance attenuation controller for turbo-generators without any linearization and the design process does not require the solution of HJI inequality. A single machine infinite bus system is firstly studied to illustrate the approach, and then multi-machine system is discussed. All the variables in the control law are locally measurable, hence the goal of decentralized control is achieved. Simulation results are given to demonstrate the effectiveness of the proposed controller.

2. Nonlinear disturbance attenuation control

Consider the following nonlinear system with uncertainty,

$$\begin{cases} \dot{x}_1 = f_1(x) + S_1(x)w_1 \\ \dot{x}_2 = f_2(x) + S_2(x)w_2 \\ \vdots \\ \dot{x}_{k-1} = f_{(k-1)}(x) + S_{(k-1)}(x)w_{(k-1)} \\ \dot{x}_k = f_k(x) + g(x)u + S_k(x)w_k \\ z = h(x) \end{cases} \quad (1)$$

where $x = (x_1, x_2, \dots, x_k)^T \in R^k$ is the state variable, $u \in R$ is the control variable, $w = (w_1, w_2, \dots, w_k)^T \in R^k$ is the disturbance, z is the regulation output, and f, g, S are smooth mappings.

The nonlinear disturbance attenuation problem for system (1) is to construct a C^1 state feedback controller $u = u(x)$ such that the corresponding close-loop system satisfies the following L_2 -gain dissipative inequality for a given positive constant γ

$$\int_0^T \|z\|^2 \leq \gamma^2 \int_0^T \|w\|^2 + V(x(0)) \quad \forall w \in L_2(0, T) \quad \forall T \geq 0 \quad (2)$$

where $V(\cdot)$ is a non-negative storage function to be constructed, $x(0)$ is the initial state, $\|\cdot\|$ denotes the

Euclidian norm of a vector, and

$$L_2(0, T) = \{w | w: [0, T] \rightarrow R^{n \times k}, \int_0^T \|w\|^2 dt < +\infty\}.$$

To solve the nonlinear disturbance attenuation problem above for system (1) is formidably difficult especially when the system scale is very large. The paper will construct the storage function via the recursive design method to obtain its solution for speed governor control systems.

3. Mathematical model for turbo-generators

(1) SMIB system

Suppose the steam turbine is of reheat type [9]. Suppose that E'_q in generator keeps constant in transient dynamics, and the dynamic model is as follows

$$\begin{cases} \dot{\delta} = \omega - \omega_0 \\ \dot{\omega} = \frac{\omega_0}{M} P_m - \frac{D}{M} (\omega - \omega_0) - \frac{\omega_0}{M} P_e + \frac{\omega_0}{M} \varepsilon_1 \\ \dot{P}_m = -\frac{1}{T_s} (P_m - P_{ms}) + \frac{1}{T_s} u_g + \frac{1}{T_s} \varepsilon_2 \\ z = \begin{bmatrix} q_1 (\delta - \delta_0) \\ q_2 (\omega - \omega_0) \end{bmatrix} \end{cases} \quad (3)$$

where δ is rotor angle (rad); ω is the rotor speed (p.u.); $\omega_0 = 2\pi f_0$ is synchronous speed (rad/s); P_m is mechanical power produced by the boiler (p.u.); P_e is the output active power of the generator set; parameters D, M and T_s are damping constant, inertia constant and time constant of the HP stage with its valving system respectively. u_g is speed governor control. ε_1 denotes

torque disturbance acting on rotating shaft of the generator set; ε_2 denotes the disturbance in the mechanical input; z is the regulation output. q_1, q_2 are positive weighing constants determined by designer. $(\delta_0, 0, P_{ms})$ is the initial operation point.

(2) Multi-machine system

Taking the same assumption as the SIMB system above, the dynamic model for multimachine power system is

$$\begin{cases} \dot{\delta}_i = \omega_i - \omega_0 \\ \dot{\omega}_i = \frac{\omega_0}{M_i} P_{mi} - \frac{D_i}{M_i} (\omega_i - \omega_0) - \frac{\omega_0}{M_i} P_{ei} + \frac{\omega_0}{M_i} \varepsilon_{1i} \\ \dot{P}_{mi} = -\frac{1}{T_{si}} (P_{mi} - P_{msi}) + \frac{1}{T_{si}} u_{gi} + \frac{1}{T_{si}} \varepsilon_{2i} \\ z_i = \begin{bmatrix} q_{1i} (\delta_i - \delta_{0i}) \\ q_{2i} (\omega_i - \omega_0) \end{bmatrix} \end{cases} \quad (4)$$

where $P_{ei} = E'_{qi} \sum_{j=1}^n E'_{qj} (B_{ij} \sin(\delta_i - \delta_j) + G_{ij} \cos(\delta_i - \delta_j))$,

the subscript i identifies the i th unit and other notations are the same as system (3).

4. Recursive design for nonlinear disturbance attenuation controller

(1) SMIB system

Firstly, set a pre-feedback as

$$u_g = P_m - P_{ms} + vT_s \quad (5)$$

where v is the new input of the system. Define the following state variables as

$$x = \begin{bmatrix} x_1 \\ x_2 \\ x_3 \end{bmatrix} = \begin{bmatrix} \delta - \delta_0 \\ \omega - \omega_0 \\ P_m \end{bmatrix} \quad (6)$$

Denote $a_1 = \frac{\omega_0}{M}$, $a_2 = -\frac{D}{M}$, $a_3 = \frac{1}{T_s}$, and introduce the

following coordinate transformation

$$\begin{cases} \hat{x}_1 = x_1 \\ \hat{x}_2 = kx_1 + x_2 \\ \hat{x}_3 = \phi(x_1, x_2, x_3) \end{cases} \quad (7)$$

where k is a given positive number and ϕ is a smooth function to be designed.

Then in the new coordinate, system (3) can be written as

$$\begin{cases} \dot{\hat{x}}_1 = -kx_1 + \hat{x}_2 \\ \dot{\hat{x}}_2 = k\dot{x}_1 + \dot{x}_2 = (k + a_2)x_2 + a_1(x_3 - P_e) + a_1\varepsilon_1 \\ \dot{\hat{x}}_3 = \frac{\partial \phi}{\partial x_1}\dot{x}_1 + \frac{\partial \phi}{\partial x_2}\dot{x}_2 + \frac{\partial \phi}{\partial x_3}\dot{x}_3 \end{cases} \quad (8)$$

Now we will seek for a storage function via recursive design and find $v = \beta(x_1, x_2, x_3)$, $\phi(x_1, x_2, x_3)$ to make the close-loop system satisfy dissipative inequality (2).

$$a. \text{ Let } V_1(\hat{x}_1, \hat{x}_2) = \frac{\sigma}{2}\hat{x}_1^2 + \frac{1}{2}\hat{x}_2^2, \quad \sigma > 0 \quad (9)$$

Introduce a function H_1 defined as

$$H_1 = \dot{V}_1|_{(8)} + \frac{1}{2}\{\|z\|^2 - \gamma^2\|\varepsilon_1\|^2\} \quad (10)$$

where

$$\dot{V}_1|_{(8)} = \sigma\hat{x}_1(-k\hat{x}_1 + \hat{x}_2) + \hat{x}_2((k + a_2)x_2 + a_1(x_3 - P_e)) + \hat{x}_2a_1\varepsilon_1,$$

denotes the differential of function $V_1(\hat{x}_1, \hat{x}_2)$ with respect to time t along the state equation of system (8).

$$\text{From (9), } \frac{1}{2}\|z\|^2 = \frac{1}{2}\{(q_1^2 + q_2^2k^2)\hat{x}_1^2 + q_2^2\hat{x}_2^2 - 2q_2^2k\hat{x}_1\hat{x}_2\}.$$

Then from (10), we can have

$$H_1 = -e\hat{x}_1^2 - \frac{1}{4}(\gamma\varepsilon_1 - \frac{2}{\gamma}a_1\hat{x}_2)^2 - \frac{\gamma^2}{4}\varepsilon_1^2 + \hat{x}_2(\mu_1x_1 + \mu_2x_2 + a_1x_3 - a_1P_e) \quad (11)$$

where

$$e = \sigma k - \frac{1}{2}q_1^2 - \frac{1}{2}q_2^2k^2, \quad \mu_1 = \frac{1}{\gamma^2}ka_1^2 + \sigma - \frac{1}{2}kq_2^2$$

$$\mu_2 = \frac{a_2^2}{\gamma^2} + a_2 + k + \frac{1}{2}q_2^2.$$

$$\text{Set } \hat{x}_3 = \phi(x_1, x_2, x_3) = \mu_1x_1 + \mu_2x_2 + x_3 \quad (12)$$

Since the second term on the right side of (11) ≤ 0 , hence

$$H_1 \leq -e\hat{x}_1^2 + \hat{x}_2\hat{x}_3 - \frac{\gamma^2}{4}\varepsilon_1^2 + \hat{x}_2(a_1x_3 - a_1P_e - x_3) \quad (13)$$

b. Similar to equation (9), set

$$V_2(\hat{x}_1, \hat{x}_2, \hat{x}_3) = \frac{\sigma}{2}\hat{x}_1^2 + \frac{1}{2}\hat{x}_2^2 + \frac{1}{2}\hat{x}_3^2 \quad (14)$$

and define

$$H_2 = \dot{V}_2|_{(8)} + \frac{1}{2}(\|z\|^2 - \gamma^2\|\varepsilon\|^2) = (\dot{V}_1|_{(8)} + \frac{1}{2}(\|z\|^2 - \gamma^2\|\varepsilon_1\|^2)) - \frac{1}{2}\gamma^2\varepsilon_2^2 + \hat{x}_3\dot{\hat{x}}_3 \quad (15)$$

where $\dot{V}_2|_{(8)}$ denotes the differential of function

$V_2(\hat{x}_1, \hat{x}_2, \hat{x}_3)$ with respect to time t along the state equations of system (8).

$$\text{Substitute } \dot{\hat{x}}_3 = \phi(x_1, x_2, x_3) = \frac{\partial \phi}{\partial x_1}\dot{x}_1 + \frac{\partial \phi}{\partial x_2}\dot{x}_2 + \frac{\partial \phi}{\partial x_3}\dot{x}_3$$

into (15), we have

$$H_2 = \dot{V}_1|_{(8)} + \frac{1}{2}(\|z\|^2 - \gamma^2\|\varepsilon_1\|^2) - \frac{1}{2}\gamma^2\varepsilon_2^2 + \hat{x}_3(\frac{\partial \phi}{\partial x_1}\dot{x}_1 + \frac{\partial \phi}{\partial x_2}\dot{x}_2 + \frac{\partial \phi}{\partial x_3}\dot{x}_3) \quad (16)$$

Similar to step a., it can be proved that

$$H_2 \leq -e_1\hat{x}_1^2 - \frac{1}{4}(\gamma\varepsilon_1 - \frac{2\hat{x}_3\mu_2a_1}{\gamma})^2 - \frac{1}{2}(\gamma\varepsilon_2 - \frac{\hat{x}_3a_3}{\gamma})^2 + \hat{x}_2(a_1x_3 - a_1P_e - x_3) + \hat{x}_3\{kx_1 + (1 + \mu_1 + \mu_2a_2)x_2 + \frac{\hat{x}_3}{\gamma^2}(\mu_2^2a_1^2 + \frac{a_3^2}{2}) + \mu_2a_1(x_3 - P_e) + v\} \quad (17)$$

Since the second and third terms on the right side of (17) ≤ 0 , from (17) it follows that

$$H_2 \leq -e_1 \hat{x}_1^2 + \hat{x}_2(a_1 x_3 - a_1 P_e - x_3) + \hat{x}_3\{kx_1 + (1 + \mu_1 + \mu_2 a_2)x_2 + \frac{\hat{x}_3}{\gamma^2}(\mu_2^2 a_1^2 + \frac{a_3^2}{2}) + \mu_2 a_1(x_3 - P_e) + v\} \quad (18)$$

Then we define

$$v = -kx_1 - (1 + \mu_1 + \mu_2 a_2)x_2 - \mu_2 a_1(x_3 - P_e) - \frac{\hat{x}_3}{\gamma^2}(\mu_2^2 a_1^2 + \frac{a_3^2}{2}) - \frac{\hat{x}_2}{\hat{x}_3}(a_1 x_3 - a_1 P_e - x_3) \quad (19)$$

and if take $\sigma \geq \frac{1}{2k}(q_1^2 + q_2^2 k^2)$, then $e_1 \geq 0$

Now from (18), we have

$$H_2 \leq -e_1 \hat{x}_1^2 \leq 0 \quad (20)$$

From equations (15) and (20), we can get

$$\dot{V}_2|_{(8)} + \frac{1}{2}\{\|z\|^2 - \gamma^2 \|e\|^2\} \leq 0 \quad (21)$$

implying

$$2V_2(x(T)) - 2V_2(x(0)) \leq \int_0^T (\gamma^2 \|e\|^2 - \|z\|^2) dt \quad \forall T > 0 \quad (22)$$

Because the storage function $V_2(x(T))$ is non-negative, we have

$$\int_0^T \|z\|^2 dt \leq \gamma^2 \int_0^T \|e\|^2 dt + 2V_2(x(0)) \quad (23)$$

Inequality (23) is called the dissipative inequality of system (3).

Now the disturbance attenuation problem for SMIB system (3) has been resolved, the control strategy is

$$\begin{cases} u_g = P_m - P_{ms} + vT_s \\ v = -k\Delta\delta - (1 + \mu_1 + \mu_2 a_2)\Delta\omega - \mu_2 a_1(P_m - P_e) - \frac{\mu_1 \Delta\delta + \mu_2 \Delta\omega - P_m}{\gamma^2}(\mu_2^2 a_1^2 + \frac{a_3^2}{2}) - \frac{k\Delta\delta_1 + \Delta\omega}{\mu_1 \Delta\delta + \mu_2 \Delta\omega - P_m}(a_1 P_m - a_1 P_e - p_m) \end{cases} \quad (24)$$

where $\Delta\delta = \delta - \delta_0$, $\Delta\omega = \omega - \omega_0$ and $k, \mu_1, \mu_2, a_1, a_2$ are defined as equations (7) and (11).

(2) Multimachine system

An n -generator power system can be considered as n interconnected sub-systems each of which can construct a function V_{2i} , $1 \leq i \leq n$ taking the form of equation (14). Then for the whole multimachine system (4), we define the storage function as

$$V(x_1, x_2, \dots, x_n) = \sum_{i=1}^n V_{2i} \quad (25)$$

then

$$\dot{V} = \sum_{i=1}^n \dot{V}_{2i}|_{(8)} \leq \frac{1}{2} \sum_{i=1}^n \{\gamma^2 \|e_i\|^2 - \|z_i\|^2\} = \frac{1}{2}(\gamma^2 \|e\|^2 - \|z\|^2) \quad (26)$$

where $\gamma = \max_{1 \leq i \leq n} \{\gamma_i\}$.

Hence

$$2V(x(T)) - 2V(x(0)) \leq \int_0^T (\gamma^2 \|e\|^2 - \|z\|^2) dt, \quad \forall T > 0 \quad (27)$$

Similar to inequality (23), we get the dissipative inequality for system (4) as follows

$$\int_0^T \|z\|^2 dt \leq \gamma^2 \int_0^T \|e\|^2 dt + 2V(x(0)) \quad (28)$$

Then the disturbance attenuation control law for multimachine system of turbo-generators is

$$\begin{cases} u_{gi} = P_{mi} - P_{msi} + v_i T_{si} \\ v_i = -k_i \Delta\delta_i - (1 + \mu_{1i} + \mu_{2i} a_{2i}) \Delta\omega_i - \mu_{2i} a_{1i} (P_{mi} - P_{ei}) - \frac{\mu_{1i} \Delta\delta_i + \mu_{2i} \Delta\omega_i - P_{mi}}{\gamma_i^2} (\mu_{2i}^2 a_{1i}^2 + \frac{a_{3i}^2}{2}) - \frac{k_i \Delta\delta_{i1} + \Delta\omega_i}{\mu_{1i} \Delta\delta_i + \mu_{2i} \Delta\omega_i - P_{mi}} (a_{1i} P_{mi} - a_{1i} P_{ei} - P_{mi}) \end{cases} \quad (29)$$

where $\Delta\delta_i = \delta_i - \delta_{0i}$, $\Delta\omega_i = \omega_i - \omega_0$ and P_{mi} are the state variables of the i th generator, and other notations have the same expression as those for the SMIB system.

In practical engineering, $\Delta\delta_i$ is usually not measured directly, so it is replaced by the integral of rotor speed, namely $\Delta\delta_i = \int_0^T \Delta\omega_i dt$, and the final control strategy is

$$\begin{aligned}
u_{gi} = & P_{mi} - P_{msi} + T_{si} \left\{ -k_i \int_0^t \Delta \omega_i d\tau - (1 + \mu_{1i} + \mu_{2i} a_{2i}) \Delta \omega_i - \right. \\
& \mu_{2i} a_{1i} (P_{mi} - P_{ei}) - \\
& \frac{\mu_{2i}^2 a_{1i}^2 + \frac{a_{2i}^2}{2}}{\gamma_i^2} (\mu_{1i} \int_0^t \Delta \omega_i d\tau + \mu_{2i} \Delta \omega_i - P_{mi}) - \\
& \frac{k_i \int_0^t \Delta \omega_i d\tau + \Delta \omega_i}{\mu_{1i} \int_0^t \Delta \omega_i d\tau + \mu_{2i} \Delta \omega_i - P_{mi}} (a_{1i} P_{mi} - a_{1i} P_{ei} - P_{mi}) \left. \right\}
\end{aligned} \quad (30)$$

where all the variables are locally measurable. Since the control law is only relevant to the local variables, it is decentralized.

5. Simulation results

A 4-machine power system, as shown in Fig.1, is studied in this paper, and the system data are listed in reference [6].

Fig. 1 A four-machine system

The speed governor control system designed according to the strategy (30) are installed on G1 to G4. In simulation, we set the disturbance attenuation level as $\gamma_i = 1$, weighting constants $q_v = 0.5$, $q_{2i} = 1$ and $k_i = 10$, $\sigma_i = 6$. In order to investigate the effectiveness of the proposed controller in improving transient stability, comparisons are made with nonlinear robust speed governor controller from reference [2], which is achieved through exact feedback linearization. System transients are stimulated by a three-phase short circuit fault occurred on line 7-8 close to bus 7, and cleared by tripping the faulted line in 0.15s. The simulation results are shown in Fig.2 to Fig.4, where the solid lines represent response of the proposed decentralized controller, the dash lines represent that of the controller

from reference [2]. It can be easily seen that the proposed controller performs better.

Fig.2 Rotor angle between generators G1 and G3

Fig.3 Terminal voltage of G1

Fig.4 Input mechanical power of G1

6. Conclusions

The paper proposes nonlinear disturbance attenuation controller for SMIB and multimachine systems of

turbo-generators respectively via a recursive design method. The design procedure does not require the solution of HJI inequality and is based on the original system without any linearization treatment. The nonlinear robust control strategy obtained for multimachine system is only relevant to the local measurement, so the decentralized controller is realized. Simulation results for a 4-machine system clearly illustrate the effectiveness of the proposed controller.

Acknowledgements

The research is supported by National Natural Science Foundation of China for Young Investigators (No. 59825104), for Oversea Young Scientists Cooperation (No. 59928705), and the National Key Basic Research Special Fund of China (No. 1998020315).

References

- [1] Lu Qiang, Sun Yuanzhang. The Nonlinear Control of Electric Power System. Beijing: Science Press, 1993
- [2] Sun Yuanzhang, Lu Qiang, Sun Chunxiao. On the Study of Power System Nonlinear Robust Control. Proceeding of the CSEE, 1996, 16(6): 361-365
- [3] D. Seto, A.M. Annaswamy, J. Bainienl. Adaptive Control of Nonlinear Systems with Triangular Structure. IEEE Trans. on AC, 1994, Vol. 39, No.7 : 1411-1428
- [4] Hu Wei, Mei Shengwei, et al. Nonlinear Adaptive Decentralized Stabilizing Control of Multi-machine System. Automation of Electric Power System, 2000, 24(21): 7-10
- [5] H. Bourles, F. Colledani, M.P. Houry. Robust Continuous Speed Governor Control for Small-signal and Transient Stability. IEEE Trans. on Power System, 1997, 12(1): 129-135
- [6] Kundur P. Power System Stability and Control. USA: McGraw-Hill Inc, 1994
- [7] Lu Qiang, Sun Yuanzhang, Mei Shengwei. The Nonlinear Control and Power System Dynamics. Kluwer Academic Publisher, 2000