University of Groningen

Discussion on

Scherpen, Jacquélien M. A.

Published in:
European Journal of Control

DOI:
[10.1016/S0947-3580\(10\)70662-2](https://doi.org/10.1016/S0947-3580(10)70662-2)

IMPORTANT NOTE: You are advised to consult the publisher's version (publisher's PDF) if you wish to cite from it. Please check the document version below.

Document Version
Publisher's PDF, also known as Version of record

Publication date:
2010

[Link to publication in University of Groningen/UMCG research database](#)

Citation for published version (APA):

Scherpen, J. M. A. (2010). Discussion on: "Stabilization of the Experimental Cart-Pendulum System with Proven Domain of Attraction". *European Journal of Control*, 16(4), 341-342. [https://doi.org/10.1016/S0947-3580\(10\)70662-2](https://doi.org/10.1016/S0947-3580(10)70662-2)

Copyright

Other than for strictly personal use, it is not permitted to download or to forward/distribute the text or part of it without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license (like Creative Commons).

The publication may also be distributed here under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license. More information can be found on the University of Groningen website: <https://www.rug.nl/library/open-access/self-archiving-pure/taverne-amendment>.

Take-down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Downloaded from the University of Groningen/UMCG research database (Pure): <http://www.rug.nl/research/portal>. For technical reasons the number of authors shown on this cover page is limited to 10 maximum.

Discussion on: “Stabilization of the Experimental Cart-Pendulum System with Proven Domain of Attraction”

Jacqueline M.A. Scherpen

Fac. Mathematics and Natural Sciences, ITM, University of Groningen, Nijenborgh 4, 9747 AG Groningen, The Netherlands

The article presents an experimental implementation of an Immersion & Invariance (I&I), [2], controller design to an experimental cart-pendulum system. The I&I controller was developed in [1], and in the paper under discussion the domain of attraction is proven to be the open upper half plane. The article serves merely as an experimental proof of principle for the I&I method, where in addition to the I&I controller, extra control actions are taken in order to deal with practical issues such as friction, and the fact that the velocities are not measured.

It is interesting to compare these results with another controller implementation on the same set up. In [5] an IDA-PBC (Interconnection and Damping Assignment Passivity Based Control) controller was developed and implemented on the same set up. Even though it is argued in the introduction of the article under discussion that the controller of [5] is rather complicated in comparison to the I&I control, the level of complexity or simplicity of the I&I controller given by expression (19) is not discussed later on in the article. For that, we can consider the IDA-PBC design of [5]. The controller expression is derived by construction of a new mass inertia matrix (M_d), interconnection matrix (J_2), and damping matrix (K_v), along with a new energy function (H_d), and the overall expression for the control law is obtained by substituting these new matrices and functions into the control law given by

$$u = (G^T G)^{-1} G^T \left(\frac{\partial H}{\partial q} - M_d M^{-1} \frac{\partial H_d}{\partial q} + J_2 M_d^{-1} p \right) - K_v G^T \frac{\partial H_d}{\partial p},$$

where $G = (0 \ 1)^T$, H is the total energy (Hamiltonian) of the uncontrolled system, and M the mass inertia matrix of the uncontrolled system. H, H_d, M, M_d, J_2 depend on the state $x = (q, p)$, where $q = (q_1, q_2)$ are the angular displacement of the pendulum, and displacement of the cart, and p the corresponding momenta. Indeed, the overall expression of the IDA-PBC controller can become more complex than the I&I controller expression of equation (19) of the paper under discussion. However, for both IDA-PBC and I&I physical considerations can be used to design the controller, and comparing the complexity of the controller design from that point of view is not straightforward.

1. Region of Attraction

Like for I&I also for IDA-PBC a PDE needs to be solved, which is done in [5]. Also similar to the I&I design, the IDA-PBC (or total energy shaping) controller in [5] is developed for the system without friction. The region of attraction of the IDA-PBC controlled system is the same as for the I&I controlled system, namely the upper half plane. However, in [5] it is shown that this would require the cart to move beyond the length of the rail, and thus the constraints of the setup do not allow for stabilization from the full upper half plane. This is also the case for the I&I implementation of the paper under discussion. Hence, in both cases first a swing up is accomplished by a bang-bang control, and then the control is switched to either the I&I or the IDA-PBC controller at 0.4 rad.

2. Friction Compensation

The I&I controller is developed for the cart-pendulum system without friction. However, it is known that the friction

of the cart with the rail cannot be neglected. No theoretical analysis of the stabilization properties of the I&I controller applied to the system with friction is given, but a simulation shows that with a friction model that is reasonable accurate, still stability is achieved. In [5] first an IDA-PBC controller is developed for the system without friction, and then the system with friction between the cart and the rail is studied. It is clarified that the pendulum system on the cart does not fulfill the dissipation condition, [3], to design an IDA-PBC controller for the system with friction. For that reason, [5] implements a friction compensation before applying IDA-PBC. Surprisingly, this is also done for the I&I controller implementation, due to limitations of the system, in particular the energy that can be provided by the actuator. The friction model that is used is the same in both cases, however, the parameters are quite different. It could be interesting to clarify this, and make a comparison between both controller implementations with the same friction compensation parameters. For both the I&I and IDA-PBC controller implementations oscillatory behaviour of the cart is seen. In the I&I case an additional integrator loop is introduced to suppress these oscillations. In other studies, such as in [4] on a different cart-pendulum setup, different solutions to deal with this are proposed.

3. Concluding Remarks

Finally, some tests with perturbations are performed on the I&I controlled set-up, and it is seen to perform reasonably well. In [5] tests are performed by not compensating fully for the friction, and for certain control parameters, the controlled system still performs reasonably well. Again,

it could be interesting to perform similar tests for both implementations. In [5] a comparison is made with a linear $\mathcal{H}_\infty$ -controller implementation, and clearly the nonlinear IDA-PBC implementation outperforms the linear one. The same is expected to hold for the I&I implementation.

The cart-pendulum system is a benchmark for many controller implementations, as mentioned in the introduction of the article under discussion, where a number of references are given. The I&I implementation is successfully implemented on the experimental setup and appears to perform well. It is of interest to compare the performance of the different controller implementations reported in the literature dealing with the cart-pendulum benchmark system.

References

1. Acosta JA, Ortega R, Astolfi A, Sarra S. A constructive solution for stabilization via immersion and invariance: the cart and pendulum system. *Automatica* 2008; 44(9): 2352–2357
2. Astolfi A, Karagiannis D, Ortega R. *Nonlinear and Adaptive Control Design and Applications*, Springer-Verlag, London, 2007
3. Gómez-Estern F, van der Schaft AJ. Physical damping in IDA-PBC controlled underactuated mechanical systems. *Eur J Control* 2004; 10: 451–468
4. Reddy CK, Witacre WW, Woolsey C. Controlled Lagrangians with gyroscopic forcing: an experimental applications. In: *Proceedings of the American Control Conference*, Boston, USA, 2004, 511–516
5. van der Burg JCM, Ortega R, Scherpen JMA, Acosta JA, Siguerdidjane HB. An experimental application of total energy shaping control: stabilization of the inverted pendulum on a cart in the presence of friction. In: *Proceedings of the European Control Conference*, Koss, Greece, 2007, 1990–1996